

MDA 700

DIGITAL TO ANALOG CONVERTER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. **SAMPLING FREQUENCY IN HZ** display: 32, 44.1, 48. **IR SENSOR.** ⚡ Touch buttons (with indicators): **INPUT 1 & 2** (optical) **3 & 4** (coaxial). Power on indicator. Touch button (with indicator): **POWER:** ON or OFF.



BACK PANEL: 2 COAXIAL and 2 OPTICAL DIGITAL AUDIO INPUTS. BALANCED and UNBALANCED AUDIO OUTPUTS. DATA: IN and OUT. POWER CONTROL: IN and OUT. Power cord receptacle.

SPECIFICATIONS: **Frequency Response:** 4Hz-22kHz (+0 -0.3dB) with sampling frequency of 48kHz; 4Hz-20kHz (+0 -0.3dB) with sampling frequency of 44.1kHz; 4Hz-15kHz (+0 -0.3dB) with sampling frequency of 32kHz. **Distortion:** 0.0015% at 1,000 Hz. **Signal to Noise Ratio:** 110dB A weighted. **Dynamic Range:** better than 100dB (1,000 Hz). **Output:** 2.2Vrms balanced and unbalanced. **Optical Inputs:** (1 and 2): 0.5 Vp-p @ 75 ohms; coaxial inputs: (3 and 4). **Power Requirements:** 120V at 20 watts.



MDA 700

DIGITAL TO ANALOG CONVERTER

McIntosh
The Compendium



MDA 700 - Sold from 1999 - 2004. S/N: RG1001~RG??? (????? UNITS)

Size: 3-5/8"H, 17-1/2"W and 15"D. **Shipping Weight:** 21 lb. **\$2,500.00**