

# MQ 108

## CUSTOM ENVIRONMENTAL EQUALIZER

McIntosh  
The Compendium



**FRONT PANEL:** Black chassis. RIGHT and LEFT unbalanced INPUTS. LEFT and RIGHT BALANCED INPUTS. Equalizer switch: IN or OUT. LED POWER indicator light. LEFT and RIGHT BALANCED OUTPUTS. RIGHT and LEFT unbalanced OUTPUTS.



**TOP PANEL:** (under) removable cover: 7 programmable boost or cut filters per channel. Filter frequency and width can be selected with plug-in capacitors. Separate controls for amplitude of each filter. Separate left and right high frequency compensation controls.



# MQ 108

## CUSTOM ENVIRONMENTAL EQUALIZER

McIntosh

The Compendium

**SPECIFICATIONS:** *Frequency Response:* 20-20kHz (+0.0 -0.5dB). *Distortion:*

0.002%. *Noise and Hum:* -105dBA. *Output Impedance:* 100 ohms balanced; 250 ohms unbalanced. *Maximum Output Voltage:* 8V. *Sensitivity:* 2.5V for rated output of 2.5V. *Input Impedance:* 22k ohms. 14 sections (7 per channel), each of which can be programmed for 1/3 octave center frequencies (narrow), or octave center frequencies (wide), from 20Hz to 1000Hz. Amplitude is continuously adjustable + or - 12dB for narrow and + or - 15dB for wide. Controls detented for flat response. *Equalizer Center Frequencies:* 50Hz, 80Hz, 150Hz, 300Hz and 600Hz. *Boost or cut range:* +12dB to -12dB and Q is adjustable from 0.6 to 4. Has no low frequency compensation for early McIntosh speakers. High frequency compensation + or - 10 dB at 20kHz. Capacitor kit not included.



**MQ 108** - Sold from 1994 - 1996. S/N: JY1001~JY???? (????? UNITS)

**Size:** 2-7/8"H, 5.65"H and 13.6"D. **Weight:** 5-1/2 lb. **\$400.00**