

6 CHANNEL AUDIO/VIDEO SYSTEM CONTROLLER (TUNER READY)

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. **INPUT.** Operating mode display: DOLBY DIGITAL, PRO LOGIC II, DTS, EXPAND, EX, NEO:6, DTS-ES, STEREO 96. **VOLUME.** ↻ **TRIM SELECT** switch: OFF, SUBWOOFER, SURROUND SPEAKER, CENTER SPEAKER, TREBLE, BASS, TUNE, DISPLAY. Digital display: INPUT, % VOLUME, SIGNAL, FREQUENCY and PRESET. **POWER GUARD** lights: LEFT FRONT, CENTER, RIGHT FRONT, LEFT SURROUND, RIGHT SURROUND. **SURROUND MODE** switch: EXTERNAL, CINEMA 2, CINEMA 1, STEREO, MUSIC 1, MUSIC 2, MUSIC 3, MUSIC 4. ↻ **CALIBRATION MIC** jack. Touch buttons: ▼TRIM / TUNE, TRIM / TUNE▲. **IR SENSOR.** Touch button: LATE NIGHT (with indicator). **HEADPHONES** jack. Touch button: **ZONE B** (with indicator). **SETUP** button. Touch buttons: **SYS OFF**, **STANDBY/ON** (with indicator), **POWER ON** and **OFF**. **AM/FM TM 1** tuner is optional.



BACK PANEL: FUSE. Power cord receptacle. ➦ COMPONENT VIDEO inputs 1 and 2: Y, PR and PB. Zone A monitor COMPONENT VIDEO outputs: Y, PR and PB. KEYPAD connectors: ZONE A and B. IR INPUTS: IR POWER switch: OFF or ON, inputs for ZONE A and ZONE B. POWER CONTROL out for ZONE A and ZONE B, Accessory, and VIDEO. ➦ DATA ports for

MHT 200

6 CHANNEL AUDIO/VIDEO SYSTEM CONTROLLER (TUNER READY)

McIntosh
The Compendium

TUNER, AUX, CD, SAT, TV, DVD, VCR 1, VCR 2, HOME, SUM, SUM A. ↗ Optical DIGITAL INPUTS: AUX, CD and SAT. Coaxial DIGITAL INPUTS: TV, DVD and VCR 1. Coaxial and optical DIGITAL OUTPUTS. RS232 POWER connector. ↗ S-video and composite VIDEO INPUTS: AUX, CD, SAT, TV, DVD, VCR 1 and VCR 2. S-video and composite VIDEO OUTPUTS: ZONE A MONITOR, VCR 1 and VCR 2. Composite VIDEO OUTPUT for ZONE B MONITOR. ↗ Analog AUDIO INPUTS: TUNER, AUX, CD, SAT, TV, DVD, VCR 1, VCR 2. Analog AUDIO OUTPUTS: ZONE A, VCR 1 RECORD, VCR 2 RECORD, ZONE B. ↗ 8-channel inputs for EXTERNAL PROCESSOR: LF, C, RF, LS, RS, BSL, BSR and SUB. PREAMP OUTPUT // POWER AMP INPUT: LF, C, RF, LS, RS, BSL, BSR. PREAMP OUTPUT for SUB. ZONE B POWER AMP INPUTS. ZONE B PREAMP OUTPUT // POWER AMP INPUTS. ↗ SPEAKER output binding posts for ZONE A: LF, C, RF, LS, RS, BSR and ZONE B Left and Right. ↗ Spaces reserved for optional **TM 1** tuner module: ANTENNA 2: external AM ANTenna (**RAA1**) and 75 Ω FM ANTenna coax input.

SPECIFICATIONS:

ZONE A -

6-channel: **120w/ch** into 4 ohms or **80w/ch** into 8 ohms.
5-channel: **130w/ch** into 4 ohms or **85w/ch** into 8 ohms.
3-channel: **140w/ch** into 4 ohms or **90w/ch** into 8 ohms.
2-channel: **160w/ch** into 4 ohms or **100w/ch** into 8 ohms.

ZONE B -

2-channel: **150w/ch** into 4 ohms or **95w/ch** into 8 ohms.

Response: 20-20kHz (+0 -0.25dB). **Distortion:** .05%. **Signal to Noise Ratio:** power amp -112dB. **Output Load Impedance:** 4 ohms or 8 ohms. **Input Impedance:** Power Amp 20k. **Input Sensitivity:** Power Amp 1.0V. **Tone Controls:** boost or cut 10dB. *Power Guard. Sentry Monitor. Direct coupled.*

Power Requirements: 120V at ?? Watts. Has hand remote **HR044** and **HR093** replacement.



MHT 200 - Sold from May 2003 - 2007. S/N: UQ1001~UQ????

Size: 9-7/16"H, 17-3/4"W and 19"D. **Weight:** 73 lb. **\$6,100.00**