

MX 132

6 CHANNEL AUDIO/VIDEO
CONTROL CENTER (TUNER READY)

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. TRIM SELECT control: OFF, SUBWOOFER, SURROUND SPEAKER, CENTER SPEAKER, TREBLE, BASS, LOUDNESS, DISPLAY. INPUT FORMAT lights: L, S, R, LFE, LS, S and RS. PROCESSING FORMAT (lighted): DTS, Dolby PRO LOGIC, DOLBY DIGITAL and THX REF. OUTPUT FORMAT (lighted): L, C, R, SUB, LS, RS. SURROUND MODE control: STEREO, MUSIC 3, MUSIC 2, MUSIC 1, CINEMA, THX CINEMA, EXTERNAL, MONO. ⚡ TRIM LEVEL control. IR sensor window. INPUT B (record) control. Digital display: ZONE B / SIGNAL strength, % VOLUME / FREQUENCY and ZONE A / PRESET. INPUT A (listen) control. VOLUME control. ⚡ Touch buttons: SYS OFF, REC LOCK (with indicator), SET UP, ▼ TUNING, TUNING ▲, AM, FM, ▼ PRESET, PRESET ▲, ENTER, LATE NIGHT (with indicator), STANDBY/ON / PRESET (with indicator), POWER ON or OFF. Has hand remote **HR 132**. AM/FM **TM 1** tuner is optional.



BACK PANEL: DIGITAL OPTICAL INPUTS: A CD 1, B SAT, C LV. DIGITAL COAXIAL INPUTS: D CD 2, E TV, F DVD. ⚡ 37 pin output for TO MULTI-ZONE CONTROLLER. AUDIO OUTPUTS: TAPE 2, TAPE 1, VCR 2, VCR 1. AUDIO INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX. Space reserved for optional **TM 1** tuner module: ANTENNA 2: external AM Antenna (**RAA1**). ⚡ RS232 CONTROL connector. Composite VIDEO OUTPUT MONITOR B. Composite and S-video OUTPUT: MONITOR A and VCR 2 & VCR 1. Composite and S-video INPUT: DVD, LV, VCR, TV, SAT, CD, TAPE, AUX. Space reserved for optional **TM 1** tuner module: 75 Ω FM Antenna coax input. ⚡ IR INPUTS for ZONE A or B external sensor. KEYPADS: ZONE A: 1 to 5 and B: 1 to 5. DATA PORTS: SUM A, SUM, HOME, DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX. ⚡

MX 132

6 CHANNEL AUDIO/VIDEO CONTROL CENTER (TUNER READY)

McIntosh

The Compendium

Power cord receptacle. POWER CONTROL: DIN MULTI-ZONE CONNECTOR, A, B and (2) ACC jacks. ZONE B OUTPUTS: BALANCED and UNBALANCED. EXTERNAL INPUTS: L SURround, CENTER, L FRONT, R SURround, SUBWOOFER, R FRONT. 25 pin MULTI-CHANNEL AMP connector. ZONE A FIXED OUTPUTS. ZONE A OUTPUTS: L SURround, CENTER, L FRONT, R SURround, SUBWOOFER, R FRONT.

PREAMPLIFIER SECTION: *Frequency Response Stereo:* Left and right small speakers: 80-20kHz; subwoofer 20Hz-80Hz; left and right large speakers: 20-20kHz; subwoofer off. *Frequency response Pro Logic:* Left, center, right small speakers: 80-20,000Hz; surround small speakers 80Hz-7kHz; subwoofer 20Hz-80Hz; left, center and right large speakers: 20-20,000Hz; Surround large speakers 20Hz -7kHz. Subwoofer off. *Frequency Response Dolby Digital and DTS:* left, center, right small speakers: 80-20,000Hz; surround small speakers 80Hz-20,000Hz; subwoofer 20Hz-80Hz; left, center and right large speakers: 20-20,000; Surround large speakers 20Hz -20,000Hz; subwoofer 20Hz-80Hz. *Frequency Response External Input:* left, center, right, left surround, right surround 20-20,000Hz; subwoofer 20Hz-120Hz. *Rated Output:* 2.0V all modes for full bit digital input. *Maximum Output Voltage:* 9.5V. *Input Impedance:* 22k ohms. *Output Impedance:* 47 ohms at all outputs. *Total Harmonic Distortion All Modes:* 0.005%. *Input Sensitivity:* 0.4V for 2.0V output. *Signal to Noise Ratio All Outputs:* >90dB un-weighted; 100dB A weighted; > 98dB CCCIR. *Maximum Input Signal:* 6V. *Voltage Gain:* 14dB analog input to output. *Tone Controls:* 12 dB boost or cut. Has **MX038** hand remote and **HR093** replacement.

WITH OPTIONAL **TM 1** AM/FM TUNER:

AM SECTION: *Sensitivity:* 20uV. *S/N:* 58dB. *Distortion:* 0.5%. *Response:* 50-6000Hz NRSC. *Adjacent Channel Selectivity:* 45dB IHF. *Image Rejection:* 65dB. *IF Rejection:* 80dB.

FM SECTION: *Sensitivity:* 1.4uV across 75 ohms. *Distortion:* 0.45% in stereo. *Response:* 20-15kHz (+0 -1.0dB). *S/N:* 75dB. *Capture Ratio:* 1.2dB. *Image Response:* 75dB. *Stereo Separation:* 45dB. *Alternate Channel Selectivity:* 75dB. *Spurious Response:* 100dB. *RF Intermodulation:* 65dB, SCA Rejection: 65dB.

Power Requirements: 120 Volts, 50/60 Hz at 65 watts.

CABINET: **L 74**



MX 132

6 CHANNEL AUDIO/VIDEO
CONTROL CENTER (TUNER READY)

McIntosh
The Compendium



MX 132 - Sold from 1999 - 2001. S/N: RH1001~RH????

Size: 7-1/16 H, 17-1/2"W and 21"D. **Weight:** 32.5 lb. **\$7,000.00**