

MX 134

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. TRIM LEVEL control. INPUT B (record) control. Digital display: ZONE B / SIGNAL strength, % VOLUME / FREQUENCY and ZONE A / PRESET. INPUT A (listen) control. VOLUME control. ⚡ TRIM SELECT control: OFF, SUBWOOFER, SURROUND SPEAKER, CENTER SPEAKER, TREBLE, BASS, LOUDNESS, DISPLAY. INPUT FORMAT lights: L, S, R, LFE, LS, S and RS. PROCESSING FORMAT (lighted): DTS, Dolby PRO LOGIC II, DOLBY DIGITAL and THX REF. OUTPUT FORMAT (lighted): L, C, R, SUB, LS, RS. SURROUND MODE control: STEREO, MUSIC 3, MUSIC 2, MUSIC 1, CINEMA, THX CINEMA, EXTERNAL, MONO. ⚡ IR sensor window. Touch buttons: SYS OFF, REC LOCK (with indicator), SET UP, ▼ TUNING, TUNING ▲, SELECT, ENTER, ◀ PRESET, PRESET ▶, BACK CHANNEL MODE, LATE NIGHT, STANDBY/ON (with indicator), POWER ON or OFF. Has hand remote **HR 044** and **HR093** replacement. AM/FM **TM 1** tuner is optional.



BACK PANEL: 37 pin TO MULTI-ZONE CONTROLLER connector. OUTPUTS: ZONE A FIXED, VCR 2 AND VCR 1. Analog INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX, TUNER. Space reserved for optional **TM 1** tuner module: ANTENNA 2: external AM Antenna (**RAA1**). ⚡ Zone A monitor COMPONENT VIDEO OUTPUTS: Y, PR and PB. COMPONENT VIDEO INPUTS (2): Y, PR and PB. Composite and S-video VIDEO OUTPUTS: ZONE B and A OUTPUT MON, VCR 2 and VCR 1. Composite and S-video VIDEO INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX. ⚡ OPTICAL and COAXIAL DIGITAL OUTPUTS. COAX DIGITAL INPUTS for CD2, TV and DVD. OPTICAL DIGITAL INPUTS for CD1, SAT and LV. DATA PORTS: SUM A, SUM, HOME, DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX, TUNER. Space reserved for optional **TM 1** tuner

MX 134

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh

The Compendium

module: 75 Ω FM Antenna coax input. ⚡ Power cord receptacle. KEYPAD connectors: ZONE A and ZONE B. IR INPUTS for external sensors: IR POWER, zone A and ZONE B. RS232 CONTROL connector. POWER CONTROL OUT for ZONE A, ZONE B, Accessory and VIDEO. ZONE B OUTPUTS. 8-channel EXTERNAL INPUTS for processor: L BACK, L SURROUND, CENTER, L FRONT, R BACK, R SURROUND, SUBWOOFER, R FRONT. 25 PIN MULTI-CHANNEL AMPLIFIER connector. ZONE A OUTPUTS: L BACK, L SURROUND, CENTER, L FRONT, R BACK, R SURROUND, SUBWOOFER, R FRONT.

PREAMPLIFIER SECTION: *Response:* 20-20kHz (+0 -0.5dB). *Distortion:* 0.005%. *Input Sensitivity and Impedance:* 22K ohms; line level: 100mV. *Voltage Gain:* 14dB main. *Signal to Noise Ratio:* Greater than 100dB A weighted. *Output:* main 2Vrms. *Output Impedance:* 47 ohms at all outputs. Has hand remote **HR044**.

WITH OPTIONAL TM 1 AM/FM TUNER:

AM SECTION: *Sensitivity:* 20uV. *S/N:* 48dB. *Distortion:* 0.5%. *Response:* 50-6000Hz (NRSC). *Adjacent Channel Sensitivity:* 55Db minimum IHF. *Image Rejection:* 65dB.

FM SECTION: *Sensitivity:* 1.4uV (14dBf). *Distortion:* 0.45% in stereo. *Response:* 20-15kHz (+0 -1.0dB). *Image Rejection:* 75dB. *Stereo Separation:* 50dB. *Alternate Channel Selectivity:* 75dB IHF.

Power Requirements: 120 Volts, at 65 watts.

CABINET: L 74



MX 134

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh

The Compendium



MX 134 - Sold from 2001 - 2004. S/N: TR1001~TR????

Size: 7-1/16 H, 17-1/2"W and 21"D. **Weight:** 32.5 lb. **\$7,100.00**