

MX 135

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh
The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. TRIM LEVEL control. INPUT B (RECORD) control (ZONE A and B): TUNER, PH/AUX, CD1, CD2, TP1, TP2, SAT, TV, LV, VCR1, VCR2, DVD. Digital display: ZONE B / SIGNAL strength, % VOLUME / FREQUENCY and ZONE A / PRESET. INPUT A (LISTEN) control. VOLUME control. ⚡ TRIM SELECT control (with indicators): OFF, SUBWOOFER, SURROUND SPEAKER, CENTER SPEAKER, TREBLE, BASS, EFFECT, DISPLAY. INPUT FORMAT lights: L, C, R, LS, LFE, RS and S. PROCESSING FORMAT (lighted): DOLBY DIGITAL, DTS, EX, DTS-ES, PRO LOGIC IIx, NEO:6, DIGITAL SIGNAL and 2 CHANNEL. OUTPUT FORMAT (lighted): L, C, R, LS, SUB, RS, LBS, BS, RBS. SURROUND MODE control: EXTERNAL, CINEMA 2, CINEMA 1, MUSIC 1, MUSIC 2, MUSIC 3, MUSIC 4. ⚡ IR sensor window. Touch buttons: SYSTEM OFF, ZONE B (with indicator), SET UP, ▼ TUNING, TUNING ▲, SELECT, ENTER, ◀ PRESET, PRESET ▶, LATE NIGHT, STANDBY/ON (with indicator), POWER ON or OFF. Has hand remote **HR 135** and **HR093** replacement. AM/FM **TM 1** tuner is optional.



BACK PANEL: 37 pin TO MULTI-ZONE CONTROLLER connector. OUTPUTS: ZONE A FIXED, VCR 2 AND VCR 1. Analog INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX, TUNER. Space reserved for optional **TM 1** tuner module: ANTENNA 2: external AM Antenna (**RAA1**). ⚡ COMPONENT VIDEO INPUTS (5): Y, PR and PB. Zone A monitor COMPONENT VIDEO OUTPUTS: Y, PR and PB. Composite and S-video VIDEO OUTPUTS: ZONE B and A OUTPUT MON, VCR 2 and VCR 1. Composite and S-video VIDEO INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX. ⚡ OPTICAL and COAXIAL DIGITAL OUTPUTS. COAX DIGITAL INPUTS for CD2, TV and DVD. OPTICAL DIGITAL INPUTS for CD1, SAT

MX 135

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh

The Compendium

and LV. DATA PORTS: SUM A, SUM, HOME, DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX, TUNER. Space reserved for optional **TM 1** tuner module: 75 Ω FM Antenna coax input. ⚡ KEYPAD connectors: ZONE A and ZONE B. IR INPUTS for external sensors: IR POWER, zone A and ZONE B. RS232 CONTROL connector. POWER CONTROL OUT for ZONE A, ZONE B, Accessory and VIDEO. ZONE B OUTPUTS. 8-channel EXTERNAL INPUTS for processor: L BACK, L SURround, CENTER, L FRONT, R BACK, R SURround, SUBWOOFER, R FRONT. 25 PIN MULTI-CHANNEL AMPLIFIER connector. ZONE A OUTPUTS: L BACK, L SURround, CENTER, L FRONT, R BACK, R SURround, SUBWOOFER, R FRONT. ⚡ Power cord receptacle. ZONE A BALANCED OUTPUTS: Right & Left BACK, Right & Left SURround, SUBWOOFER, CENTER, Right & Left FRONT. ZONE A BALANCED INPUTS: Right & Left 2 and 1.

PREAMPLIFIER SECTION: *Response:* 20-20kHz (+0 -0.5dB). *Distortion:* 0.005%.

Input Sensitivity and Impedance: 22K ohms; line level: 500mV unbalanced and 50K ohms, 1V unbalanced; Phono MM 5mV (50mV max) at 47k and 65pF. *Voltage Gain:* 14dB main. *Signal to Noise Ratio:* Greater than 96dB A weighted. *Output:* main 2.5Vrms unbalanced, 5Vrms balanced. *Output Impedance:* 100 ohms unbalanced and 200 ohms balanced at all outputs.

WITH OPTIONAL TM 1 AM/FM TUNER:

AM SECTION: *Sensitivity:* 20uV. *S/N:* 48dB. *Distortion:* 0.5%. *Response:* 50-6000Hz (NRSC). *Adjacent Channel Sensitivity:* 55Db minimum IHF. *Image Rejection:* 65dB.

FM SECTION: *Sensitivity:* 1.4uV (14dBf). *Distortion:* 0.45% in stereo. *Response:* 20-15kHz (+0 -1.0dB). *Image Rejection:* 75dB. *Stereo Separation:* 50dB. *Alternate Channel Selectivity:* 75dB IHF.

Power Requirements: 120 Volts, 50/60 Hz at 65 watts.



MX 135 - Sold from March 2004 - 2007. S/N: VJ1001~VJ????

Size: 9-7/16"H, 17-3/4"W and 18-3/4"D. *Weight:* 31 lb. **\$7,600.00**