

MX 136

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh
The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. TRIM LEVEL control. INPUT B (RECORD) control (ZONE A and B): TUNER, PH/AUX, CD1, CD2, TP1, TP2, SAT, TV, LV, VCR1, VCR2, DVD. Digital display: ZONE B / SIGNAL strength, % VOLUME / FREQUENCY and ZONE A / PRESET. INPUT A (LISTEN) control. VOLUME control. ⚡ TRIM SELECT control (with indicators): OFF, SUBWOOFER, SURROUND SPEAKER, CENTER SPEAKER, TREBLE, BASS, EFFECT, DISPLAY. INPUT FORMAT lights: L, C, R, LS, LFE, RS and S. PROCESSING FORMAT (lighted): DOLBY DIGITAL, DTS, EX, DTS ES, PRO LOGIC IIx, NEO : 6, DIGITAL SIGNAL and 2 CHANNEL. OUTPUT FORMAT (lighted): L, C, R, LS, SUB, RS, LBS, BS, RBS. SURROUND MODE control: EXTERNAL, CINEMA 2, CINEMA 1, STEREO, MUSIC 1, MUSIC 2, MUSIC 3, MUSIC 4. ⚡ IR sensor window. Touch buttons: SYSTEM OFF, ZONE B (with indicator), SET UP, ▼ TUNING, TUNING ▲, SELECT, ENTER, ◀ PRESET, PRESET ▶, LATE NIGHT, STANDBY / ON (with indicator), POWER ON or OFF. Has hand remote **HR 136** and **HR093** replacement. AM/FM **TM 1** tuner is optional.



BACK PANEL: HDMI VIDEO: MON A OUT, 4, 3, 2, 1. OUTPUTS: ZONE A FIXED, VCR 2 AND VCR 1. Analog INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX, TUNER. Space reserved for optional **TM 1** tuner module: ANTENNA 2: external AM ANTENNA (**RAA1**). ⚡ COMPONENT video INPUTS (5): PR, PB and Y. MONITOR A COMPONENT VIDEO OUTPUTS: PR, PB and Y. Composite and S-video VIDEO OUTPUTS: ZONE B and A

MX 136

8 CHANNEL AUDIO/VIDEO PRE-AMP (TUNER READY)

McIntosh

The Compendium

OUTPUT MON, VCR 2 and VCR 1. Composite and S-video VIDEO INPUTS: DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX. ⚡ OPTICAL and COAXIAL DIGITAL OUTPUTS. COAX DIGITAL INPUTS for CD2, TV and DVD. OPTICAL DIGITAL INPUTS for CD1, SAT and LV. DATA PORTS: SUM A, SUM, HOME, DVD, VCR 2, VCR 1, LV, TV, SAT, TAPE 2, TAPE 1, CD 2, CD 1, AUX, TUNER. Space reserved for optional **TM 1** tuner module: 75 Ω FM Antenna coax input. ⚡ KEYPAD connectors: ZONE A and ZONE B. IR INPUTS for external sensors: IR POWER, zone A and ZONE B. RS232 CONTROL connector. POWER CONTROL OUT for ZONE A, ZONE B, Accessory and VIDEO. ZONE B OUTPUTS. 8-channel EXTERNAL INPUTS for processor: L BACK, L SURROUND, CENTER, L FRONT, R BACK, R SURROUND, SUBWOOFER, R FRONT. 25 PIN MULTI-CHANNEL AMPLIFIER connector. ZONE A OUTPUTS: L BACK, L SURROUND, CENTER, L FRONT, R BACK, R SURROUND, SUBWOOFER, R FRONT. ⚡ Power cord receptacle. ZONE A BALANCED OUTPUTS: Right & Left BACK, Right & Left SURROUND, SUBWOOFER, CENTER, Right & Left FRONT. ZONE A BALANCED INPUTS: Right & Left 2 and 1.

PREAMPLIFIER SECTION: Response: 20-20kHz (+0 -0.5dB). **Distortion:** 0.005%.

Input Sensitivity and Impedance: 22K ohms; line level: 500mV unbalanced and 50K ohms, 1V unbalanced; Phono MM 5mV (50mV max) at 47k and 65pF. **Voltage Gain:** 14dB main. **Signal to Noise Ratio:** Greater than 96dB A weighted. **Output:** main 2.5Vrms unbalanced, 5Vrms balanced. **Output Impedance:** 100 ohms unbalanced and 200 ohms balanced at all outputs.

WITH OPTIONAL TM 1 AM/FM TUNER:

AM SECTION: Sensitivity: 20uV. **S/N:** 48dB. **Distortion:** 0.5%. **Response:** 50-6000Hz (NRSC). **Adjacent Channel Sensitivity:** 55Db minimum IHF. **Image Rejection:** 65dB.

FM SECTION: Sensitivity: 1.4uV (14dBf). **Distortion:** 0.45% in stereo. **Response:** 20-15kHz (+0 -1.0dB). **Image Rejection:** 75dB. **Stereo Separation:** 50dB. **Alternate Channel Selectivity:** 75dB IHF.

Power Requirements: 120 Volts, 50/60 Hz at 65 watts.



MX 136 - Sold from April 2007 - 2010. S/N: XM1001~XM????

Size: 9-7/16"H, 17-1/2"W and 18-3/4"D. **Weight:** 31 lb. **\$9,500.00**