

MX 151

AUDIO/VIDEO CONTROL CENTER

McIntosh

The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. INPUT control. Digital information display. VOLUME control. ⚡ TRIM SELECT control. INPUT FORMAT indicators: L, C, R, LS, LFE, RS, LBS, S and RBS. Indicators: ANALOG SIGNAL, ROOMPERFECT, DIGITAL SIGNAL, HD AUDIO. OUTPUT FORMAT indicators: L, C, R, LS, SUB, RS, LBS, BS, RBS. SURROUND MODE control. ⚡ IR sensor. Touch buttons: DISPLAY MODE, LATE NIGHT, SET UP, ▼ADJUST ▲, BACK, SELECT, ◀NAVIGATE ▶, ZONE B CONTROL (with indicator), STANDBY / ON (with indicator).



BACK PANEL: COMPONENT VIDEO inputs 1 through 5: Y/G, PB/B and PR/R. Zone A composite VIDEO/S-VIDEO inputs: 1 and 2. ⚡ HDMI inputs 1 through 5. RS232 CONTROL connector. NET connector. USB connector. ⚡ COMPONENT VIDEO outputs: Y/G1, PB/B1 and PR/R1, Y/G2, PB/B2 and PR/R2. Zone A composite VIDEO outputs: 1 and 2, s-VIDEO outputs: 1 and 2. COMPACT FLASH receptacle. ⚡ MULTICHANNEL inputs: Left front, Left surround, center, Left Back surround / Right front, Right surround, Low Frequency Effects, Right Back surround. MICROPHONE input. DIGITAL AUDIO inputs: 1 / 2, 3 / 4. ZONE A OUTPUTS (balanced): AUX 1, AUX 2, Left front, center, Left surround, Left Back surround. ⚡ BALANCED AUDIO inputs: Left & Right 1. UNBALANCED STEREO AUDIO inputs: Left & Right 1, 2, 3, 4. DIGITAL AUDIO inputs: AES 5 EBU, optical 6, 7, 8, 9. ZONE B OUTPUT: Left & Right. ZONE A OUTPUTS (unbalanced): AUX 3 / AUX 4, Left front / Right front, center / sub, surround Left / surround Right, Left Back surround / Right Back surround. ZONE A OUTPUTS (balanced): Right front, sub, Right surround, Right

MX 151

AUDIO/VIDEO CONTROL CENTER

McIntosh

The Compendium

Back surround. ⚡ BALANCED AUDIO INPUTS: Left & Right 2. GROUND connector. SENSORS: ZONE A and ZONE B. IR INPUTS: zone A and zone B. DATA OUTPUTS: 1 / 2, 3 / 4, 5 / 6, 7 / 8, SUM A / SUM B. TRIGGER INPUTS: 1 / 2. PC OUTPUTS: 1 / 2. TRIGGER OUTPUTS: 1 / 2, 3 / 4. AUXILIARY CONTROL. Power cord receptacle.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB) Left, Right, Left Surround, Right Surround, Left Back Surround, Right Back Surround; 20-8kHz (+0 -0.5dB) Subwoofer. **Total Harmonic Distortion:** 0.005% maximum from 20Hz to 20,000Hz at rated output. **Signal to Noise Ratio:** High Level 96dB; Phono 86dB below 10mV input. **Rated Output Voltage:** main 2.5V unbalanced; 5.0V balanced. **Maximum Voltage Output:** 6.5V Unbalanced outputs (8.5V Subwoofer); 13V Balanced outputs (17V Subwoofer). **Output Impedance:** 75 ohms Unbalanced and 100 ohms Balanced. **Input Sensitivity and Impedance:** 10K ohms, High Level: 500mV Unbalanced and 1V Balanced; Phono MM 5mV (50mV max) at 47k and 65pF. **Voltage Gain:** High Level 14dB; Phono 54 dB. **Tone Controls:** Bass Control - ± 10 dB at 30Hz; Treble Control - ± 10 dB at 10,000Hz.

Power Requirements: 120 Volts, 50/60 Hz at 75 watts. Has hand remote **HR070**.

FEATURES: HDMI video switching with 3D Video Pass-Through. RoomPerfect environmental audio correction. HD Digital audio decoding for Dolby TrueHD and DTS-HD Master Audio. 2-Channel source material can be played back in Stereo or processed up to 7.;1 multi-channel using Dolby Pro Logic IIx or DTS Neo:6 decoding. Built-in Dual Zone. Assignable balanced input and outputs, analog phono section, base and treble tone controls and full RoomPerfect room correction.



MX 151 - Sold from April 2012 - 2016. S/N: ABS1001~ABS????

Size: 7-5/8"H, 17-1/2"W and 19-1/2"D. **Weight:** 31 lb. **\$12,500.00**