

MA 6400

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. TREBLE. Left POWER OUTPUT meter (linear WATTS or DECIBELS). POWER GUARD light. INPUT SELECTOR: CD 1, CD 2, TUNER, VIDEO and PH/AUX. Right POWER OUTPUT meter (linear WATTS or DECIBELS). POWER GUARD light. VOLUME. Mute light. ⚡ BASS. IR sensor. Pushbutton switches with indicator lights: TAPE MON 1, TAPE MON 2, TAPE COPY: 1 to 2 and 2 to 1. HEADPHONES jack. Pushbutton switches with indicator lights: MONO, SPEAKERS: 1 and 2, and POWER. Concentric BALANCE: L to R / LOUDNESS: FLAT to MAX.



BACK PANEL: DIN control connector: CD 1. DATA ports: TUNER, CD 2, CD 1, AUX, SUM, TAPE 2, TAPE 1, VIDEO. POWER AMP IN. POWER AMP INPUT switch: EXTERNAL or INTERNAL. OUTPUTS: MAIN, TAPE 2, TAPE 1. PROCESSOR: FROM. PROCESSOR switch: IN or OUT. PROCESSOR: TO. INPUTS: TAPE 2, TAPE 1, VIDEO, TUNER, CD 2, CD 1, AUX. SELECTOR switch: AUX or PH. INPUT: PH. ⚡ FUSE. Power cord. AC outlets: 1 SWITCHED, 1 UNSWITCHED. LEFT & RIGHT output barrier strips for SPEAKERS 1 and 2. Coax EXTERNAL SENSOR connector. POWER CONTROL jack. Ground binding post.

SPECIFICATIONS: 100w/ch at 4 ohms. **Response:** 20-20kHz (+0 -0.5dB).

Distortion: 0.005%. **Dynamic Headroom:** 2.4dB. **Noise and Hum:** -100dB high level, -90dB low level re 10mV. **Damping Factor:** 40. **Input Sensitivity and Impedance:** high level 0.25V (10V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF, power amp 2.5V. Bass and treble boost or cut 12dB. Sentry Monitor. Direct coupled. Power Guard. **Power Requirements:** 120V at 5 Amps. Has hand remote **HR033** and **HR093** replacement.

CABINET: L 82

MA 6400

STEREO INTEGRATED AMPLIFIER

McIntosh
The Compendium



MA 6400 - Sold from 1995 - 1997. S/N: MF1001~MF????

Size: 5-3/8"H, 17-1/2"W and 18-1/8"D. **Weight:** 41 lbs. **\$3,500.00**