

MA 6600

STEREO INTEGRATED AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. Left POWER OUTPUT meter (LINEAR WATTS or DECIBELS). Left and right POWER GUARD lights. Right POWER OUTPUT meter (LINEAR WATTS or DECIBELS). ⚡ INPUT selector. TRIM SELECT control. Digital display. TRIM ADJUST control. VOLUME. ⚡ 1/4" HEADPHONES jack. Touch buttons: STORE/EXIT (with indicator), MONO/SETUP (with indicator), BYPASS (with indicator), MUTE, OUTPUT 1 & 2 (with indicator). STANDBY/ON / RESET (with indicator).



BACK PANEL: Right speaker OUTPUT connectors for 2, 4 and 8 OHMS. Tuner module receptacle/balanced CD 1 INPUTS. Left speaker OUTPUT connectors for 2, 4 and 8 OHMS. ⚡ Power cord receptacle. FUSE. POWER CONTROL connectors: MAIN, Accessory, POWER CONTROL 1 and 2. Coax EXTERNAL SENSOR connector. DATA PORTS: CD1, CD2, DVD, TV, SERVER, REC, Inputs: PHONO. Ground binding post. Inputs: CD2, DVD, TV, SERVER, REC, jumper: POWER AMP input. Outputs: jumper: 1, 2, REC.

SPECIFICATIONS: 200w/ch into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.005%. **Output Impedance:** 2, 4 or 8 ohms. **Dynamic Headroom:** 2.0dB. **Noise and Hum:** 115dB power amp, -92dB high level, -84dB phono re 5mV. **Damping Factor:** >40. **Input Sensitivity and Impedance:** high level 0.25V (8V max unbalanced, 16V balanced) at 20k, phono 2.5mV (80mV max) at 47k and 65pF, power amp 16V at 10k. **Power Guard.** **Sentry Monitor.** **Autoformers.** **Power Requirements:** 120V at 4.4 Amps. Has hand remote **HR058** and **HR093** replacement.

MA 6600

STEREO INTEGRATED AMPLIFIER

McIntosh
The Compendium



MA 6600 - Sold from 2008 -2016. S/N: YU1001~YU????

Size: 9-7/16"H, 17-1/2"W and 22"D. **Weight:** 75 lbs. **\$5,500.00**