

MA 6850

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Left and right **POWER OUTPUT** meters (linear WATTS or DECIBELS). ⚡ **TREBLE**. **RECORD SELECTOR** with indicator lights: **AUX**, **CD 1**, **CD 2**, **TUNER**, **TAPE 1**, **TAPE 2**, **TAPE 3**, **VIDEO**. Left **POWER GUARD** light. IR sensor. Digital **VOLUME** readout. Right **POWER GUARD** light. **LISTEN SELECTOR** with indicator lights: **AUX**, **CD 1**, **CD 2**, **tuner**, **TAPE 1**, **TAPE 2**, **TAPE 3**, **VIDEO**. **VOLUME**. ⚡ **BASS**. Pushbutton switches with indicator lights: **MONO**, **LISTEN PROC**, **RECORD PROC**, **RECORD MON**. **POWER**: OFF or ON. Pushbutton switches with indicator lights: **MUTE**, **SPEAKERS 1 and 2**, and **STANDBY/ON**. Concentric **BALANCE / LOUDNESS**: FLAT to MAX.



BACK PANEL: **LISTEN** jacks: **POWER AMP IN**. **POWER AMP INPUT** switch: **EXTERNAL** or **INTERNAL**. **LISTEN** jacks: **PREAMP OUT**. **PROCESSOR**: **FROM** and **TO**. **RECORD** jacks: **TAPE 3**, **TAPE 2**, **TAPE 1**, **PROCESSOR**: **FROM** and **TO**. **INPUTS**: **VIDEO**, **TAPE 3**, **TAPE 2**, **TAPE 1**, **TUNER**, **CD 2**, **CD 1**, **AUX**. ⚡ Coax **EXTERNAL SENSOR** connector. speaker control relay connector. **POWER** control jack. **DATA PORTS**: **SUM**, **VIDEO**, **TAPE 3**, **TAPE 2**, **TAPE 1**, **TUNER**, **CD 2**, **CD 1**, **AUX**, **HOME**. ⚡ Power cord receptacle. **FUSE**. **RIGHT** output **SPEAKER** connectors for 2, 4 and 8 ohms. **LEFT** output **SPEAKER** connectors for 2, 4 and 8 ohms.

MA 6850

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 150w/ch. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.005%. **Output Impedance:** 2, 4 and 8 ohms. **Dynamic Headroom:** 1.8dB. **Noise and Hum:** 110dB power amp, -100dB high level, -90dB low level re 10mV. **Damping Factor:** 40. **Input Sensitivity and Impedance:** high level 0.25V (10V max) at 22k, power amp 1.4V. **Bass and Treble Boost or Cut:** 12dB. **Power Guard.** **Sentry Monitor.** **Autoformers.** **Power Requirements:** 120V at 6.5 Amps. Same as the **MA 6800** but without headphone output and phono preamp. Has hand remote **HR033** and **HR093** replacement.

CABINET: L 84



MA 6850 - Sold from 1998 - 2001. S/N: PE1001~PE????

Size: 7-1/16"H, 17-1/2"W and 20"D. **Weight:** 70 lbs. **\$3,500.00**