

MC 3500

MONAURAL TUBE POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Black and anodized aluminum panel. Illuminated **METER:** monitors **OUTPUT VOLTAGE**, **DECIBELS** or **CATHODE CURRENT** for each output tube. ⚡ **INPUT** connectors: RCA and BNC. **GAIN CONTROL**. **METER RANGE SWITCH:** OFF, VOLTS, dB, dB-10 or V1-V8. **POWER CIRCUIT BREAKER:** ON or OFF. **OUTPUT RANGE SWITCH:** 1, 4, 8, 16, 50, and 64 OHMS with corresponding voltages 17.3, 35.8, 53.0, 75.0, 132 and 150V. Dual banana **OUTPUT** connectors. Heavy duty handles.



BACK PANEL: Cooling fan. ⚡ Power cord receptacle. FUSE. LINE VOLTAGE SWITCH: 117 or 125V. Speaker **OUTPUT 1** and **2** barrier strip. **TRANSFORMER INPUT**. Audio **INPUT 1** and **2** terminals. **SUBSONIC FILTER** switch: OUT or IN.

TUBES: 8-**6LQ6/6JE6B** output, 2-**12AX7/ECC83**, 2-**6DJ8/ECC88**, **6CG7/6FQ7** and **6BL7GTA**. Solid state rectifier bridge. Direct coupled.

MC 3500

MONAURAL TUBE POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 350w. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.15%.
Noise & Hum: - 95dB. **Output Impedance:** 1, 4, 8, 16, 50 and 64 ohms. All impedances can be isolated from ground. **Internal Impedance:** less than 5% of rated impedance. **Input Impedance:** 200k. **Input Sensitivity:** 1.1V.



MC 3500 - Sold from February 1968 - June 1971. S/N: 10N01~11N95 (193 UNITS)

Size: 19" rack mounting. 10-1/2"H, and 17"D behind panel. **Weight:** 125 lb. **\$1,099.00**