

MC 7205

FIVE CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. 5 POWER GUARD lights – one for each channel. 6 meter lights – indicates which channel the meter is reading. ⚡ Three switchable illuminated POWER OUTPUT meters (linear WATTS). ⚡ METER switch: LIGHTS OFF, SUMMED, FRONT / CTR, SURR / SUB. POWER switch: OFF, REMOTE or ON.



BACK PANEL: Power cord receptacle. FUSE. [Right front and surround section: RIGHT FRONT and RIGHT SURROUND INPUTS. RIGHT SURROUND and RIGHT FRONT LEVEL controls: 2.5V to 1.0V. Speaker output terminals: RIGHT SURROUND and RIGHT FRONT]. [Subwoofer and center channel section: SUB IN/OUT and CTR INPUT. SUB METER CAL and center LEVEL controls: 2.5V to 1.0V. Speaker output terminal: center]. THX 26 pin INPUT connector. POWER CONTROL jacks: IN and OUT. [Left surround and front section: LEFT SURROUND and LEFT FRONT INPUTS. LEFT SURROUND and LEFT FRONT LEVEL controls: 2.5V to 1.0V. Speaker output terminals: LEFT SURROUND and LEFT FRONT].

SPECIFICATIONS: Five channels. **200w/ch** into 4 ohms. **120w/ch** into 8 ohms.

Response: 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Noise and Hum:** -113dBA. **Output Impedance:** 4 or 8 ohms. **Damping Factor:** 100 at 4 ohms or 200 at 8 ohms. **Input Impedance:** 10k. **Input Sensitivity:** 1v. Sentry Monitor. Power Guard. Direct coupled. THX Certified.

CABINET: L 84

MC 7205

FIVE CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



MC 7205 - Sold from 1998 - 2001. S/N: NJ1001~NJ????

Size: 7-1/16"H, 17-1/2"W and 21"D. **Weight:** 53 lb. **\$4,500.00**