

C 1000

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



C 1000C – CONTROLLER FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. **BALANCE:** L to R. Digital display. **VOLUME.** ⚡ **RECORD SELECT.** IR sensor. Touch buttons (with indicator lights): **SETUP**, **RECORD MONITOR**, **MUTE**, **STANDBY/ON RESET**. **LISTEN SELECT.**



C 1000C – CONTROLLER BACK PANEL: Power cord receptacle. **EXTERNAL SENSOR** connector. **TRIGGERS;** B/SPKR2 and A/SPKR1 **OUTPUTS.** 2 **POWER CONTROL MAIN** outputs. **PASS THRU** power control input. **DATA PORTS:** PROG SUM, 7-D/A, 6-CD, 5-CDR, 4-SRVR, 3-TUNER, 2-AUX, 1-DVD. ⚡ **RIGHT** and **LEFT SLO-BLOW** fuses. 21-conductor: **RIGHT CONTROLLER OUTPUT A** connector. **RIGHT CONTROLLER OUTPUT C** connector. **LEFT CONTROLLER OUTPUT B** connector. **LEFT CONTROLLER OUTPUT D** connector.

S/N: WF1001~WF????

Size: 6"H, 17-1/2"W and 24"D behind panel. **Weight:** 39 pounds.

C 1000

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



C 1000P – SOLID STATE PREAMPLIFIER FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. Left channel OUTPUT LEVEL meter (dB). Right channel OUTPUT LEVEL meter (dB). ⚡ HEADPHONES jack.



C 1000P – SOLID STATE PREAMPLIFIER BACK PANEL: (Balanced): MAIN RIGHT channel OUTPUTS. CDR (5) RIGHT channel OUTPUTS. CD (6) RIGHT channel INPUTS. CDR (5) RIGHT channel INPUTS. 21-conductor PREAMPLIFIER CONTROL INPUT A and B. (Balanced): CDR (5) LEFT channel INPUTS. CD (6) LEFT channel INPUTS. CDR (5) LEFT channel OUTPUTS. MAIN LEFT channel OUTPUTS. ⚡ (Balanced): MAIN/SPEAKER1 and MAIN/SPEAKER 2 RIGHT channel OUTPUTS. DA (7) RIGHT channel INPUTS. RECORD LINK RIGHT channel INPUTS. RECORD LINK LEFT channel INPUTS. DA (7) LEFT channel INPUTS. MAIN/SPEAKER1 and MAIN/SPEAKER 2 LEFT channel OUTPUTS. ⚡ (Unbalanced): SPEAKER1 and SPEAKER 2 RIGHT channel OUTPUTS. ⚡ server (4) and CDR (5) RIGHT channel OUTPUTS. ⚡ PROCESSOR RIGHT channel LISTEN TO and FROM. ⚡ PROCESSOR RIGHT channel RECORD TO and FROM. ⚡ TUNER (3) and server (4) RIGHT channel INPUTS. ⚡ DVD (1) and AUX (2) RIGHT channel INPUTS. ⚡ PHONO INPUTS MM (8) and MC (9) RIGHT channel INPUTS. 2 PHONO Ground connectors. ⚡ PHONO INPUTS MM (8) and MC (9) LEFT channel INPUTS. ⚡ DVD (1) and AUX (2) LEFT channel INPUTS. ⚡ TUNER (3) and server (4) LEFT channel INPUTS. ⚡ PROCESSOR LEFT channel RECORD TO and FROM. ⚡ PROCESSOR RIGHT channel LISTEN TO and FROM. ⚡ server (4) and CDR (5) LEFT channel OUTPUTS. SPEAKER1 and SPEAKER 2 LEFT channel OUTPUTS.

C 1000

STEREO PRE-AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: **Response:** 10-40kHz (+0 -0.5dB). **Distortion:** 0.002% from 20 to 20,000 Hz. **Signal to Noise Ratio:** 100dB high level, -88 dB phono. **Maximum Output:** 12V RMS unbalanced, 25V RMS balanced. **Output Impedance:** 220 ohms. **Input Sensitivity and Impedance:** high level 0.45V (5V max) at 22k unbalanced and 10V balanced, MM phono: 4.5mV (50mV max) at 47k and 50 to 750 pF, in 50 pF steps, MC phono: .45mV (5mV max) at 25, 50, 100, 200, 400 or 1,000 ohms: 100 pF. **Power Requirements:** 120V at 120 Watts. Has **HR054** and **HR1000** remote controls and **HR093** replacement.

S/N: WH1001~WH????

Size: 6"H, 17-1/2"W and 24"D behind panel. **Weight:** 33 pounds.



C 1000T – TUBE PREAMPLIFIER FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. Left channel OUTPUT LEVEL meter (dB). Tubes can be seen through the clear rectangles between the meters. Right channel OUTPUT LEVEL meter (dB). ⚡ HEADPHONES jack.



C 1000T – TUBE PREAMPLIFIER BACK PANEL: (Balanced): MAIN RIGHT channel OUTPUTS. CDR (5) RIGHT channel OUTPUTS. CD (6) RIGHT channel INPUTS. CDR (5) RIGHT channel INPUTS. 21-conductor PREAMPLIFIER CONTROL INPUT C and D. (Balanced): CDR (5) LEFT channel INPUTS. CD (6) LEFT channel INPUTS. CDR (5) LEFT channel OUTPUTS. MAIN LEFT channel OUTPUTS. ⚡ (Balanced): MAIN/SPEAKER1 and MAIN/SPEAKER 2 RIGHT channel OUTPUTS. DA (7) RIGHT channel INPUTS. RECORD LINK RIGHT channel INPUTS. RECORD LINK LEFT channel INPUTS. DA (7) LEFT channel INPUTS. MAIN/SPEAKER1 and MAIN/SPEAKER 2 LEFT channel OUTPUTS. ⚡

C 1000

STEREO PRE-AMPLIFIER

McIntosh

The Compendium

(Unbalanced): SPEAKER1 and SPEAKER 2 RIGHT channel OUTPUTS. ⚡ SERVER (4) and CDR (5) RIGHT channel OUTPUTS. ⚡ PROCESSOR RIGHT channel LISTEN TO and FROM. ⚡ PROCESSOR RIGHT channel RECORD TO and FROM. ⚡ TUNER (3) and SERVER (4) RIGHT channel INPUTS. ⚡ DVD (1) and AUX (2) RIGHT channel INPUTS. ⚡ PHONO INPUTS MM (8) and MC (9) RIGHT channel INPUTS. 2 PHONO GROUND connectors. ⚡ PHONO INPUTS MM (8) and MC (9) LEFT channel INPUTS. ⚡ DVD (1) and AUX (2) LEFT channel INPUTS. ⚡ TUNER (3) and SERVER (4) LEFT channel INPUTS. ⚡ PROCESSOR LEFT channel RECORD TO and FROM. ⚡ PROCESSOR RIGHT channel LISTEN TO and FROM. ⚡ SERVER (4) and CDR (5) LEFT channel OUTPUTS. SPEAKER1 and SPEAKER 2 LEFT channel OUTPUTS.

SPECIFICATIONS: **Response:** 10-20kHz (+0 -0.5dB). **Distortion:** 0.08% from 20 to 20,000 Hz. **Signal to Noise Ratio:** 93dB high level, -80 dB phono. **Maximum Output:** 8V RMS unbalanced, 16V RMS balanced. **Output Impedance:** 220 ohms. **Input Sensitivity and Impedance:** high level 0.45V (5V max) at 22k unbalanced and 10V balanced, MM phono: 4.5mV (50mV max) at 47k and 50 to 750 pF, in 50 pF steps, MC phono: .45mV (5mV max) at 25, 50, 100, 200, 400 or 1,000 ohms: 100 pF. Has **HR054** and **HR1000** remote controls.

S/N: WH1001~WH????

Size: 6"H, 17-1/2"W and 24"D behind panel. **Weight:** 34 pounds.



C 1000 -Sold from 2005 - 2018.

Both preamp and power controller **\$16,000.00 to \$23,000**

C1000P - **\$9,000.00**

C1000T - **\$9,000.00**

C1000C - **\$8,000.00**