

# C 2200

STEREO PRE-AMPLIFIER /  
VIDEO CONTROL CENTER

# McIntosh

The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. **INPUT.** Illuminated left and right **OUTPUT LEVEL** meters (DECIBELS). **VOLUME.** ⚡ **BASS.** **TREBLE.** Digital display. **METER LIGHTS:** ON or OFF / **SETUP.** **BALANCE:** L to R. ⚡ **IR SENSOR.** Touch buttons: **TONE BYPASS,** **MONO,** **RECORD MONITOR,** **SETUP.** **HEADPHONES** jack. Touch buttons: **MUTE,** (with indicators): **OUTPUTS 1,** **OUTPUTS 2,** **STANDBY/ON.** **POWER** switch: ON or OFF.



**BACK PANEL:** Left and right balanced **OUTPUTS:** **MAIN,** **2,** and **1.** Left and Right balanced **INPUTS:** **VCR,** **SAT,** **DVD** and **CD.** Ground binding post. ⚡ Left and Right unbalanced **OUTPUTS:** **MAIN,** **2,** **1** and **TAPE/REC.** Unbalanced **INPUTS:** **TAPE/REC,** **VCR,** **SAT,** **DVD,** **CD,** **CD 2,** **TUNER** and **PH/AUX.** ⚡ Power cord receptacle. **FUSE.** **POWER CONTROL** outputs: **MAIN,** **ACC,** **2** and **1.** **PASS THRU** power control. Coax **EXTERNAL SENSOR** connector. **DATA PORTS:** **TAPE,** **VCR,** **SAT,** **DVD,** **CD,** **CD 2,** **TUNER.**

**SPECIFICATIONS:** **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.08%. **Noise and Hum:** - 93dB high level, -80dB phono. **Maximum Output:** 8V unbalanced, 16V balanced. **Output Impedance:** 500 ohms balanced and 250 ohms unbalanced. **Input Sensitivity and Impedance:** high level 0.45V (2.5V max) at 22k unbalanced and 44k balanced, phono MM 4.4mV (50mV max) at 47k and 65pF. **Power Requirements:** 120V at 75 Watts. Has hand remote **HR044** and **HR093** replacement.

**TUBES:** 4-**12AX7A,** 4-**12AT7A.** Solid state rectifier bridges.

# C 2200

**STEREO PRE-AMPLIFIER /  
VIDEO CONTROL CENTER**

**McIntosh**  
The Compendium



**C 2200** -Sold from 2001 - 2009. S/N: TS1001~TS????

**Size:** 7-5/8"H, 17-1/2"W and 20"D behind panel. **Weight:** 26-3/4 lb.  
**\$4,600.00**