

# C 31V

## STEREO PRE-AMPLIFIER – VIDEO CONTROL CENTER

**McIntosh**  
The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature and anodized black aluminum panel. Indicator lights: CD, LASER, TV, TUNER, PHONO, AUX 1, AUX 2. VCR/T 1 and VCR/T 2, VCR/T COPY: 1►2 or 2►1, MONO, SPEAKER: 1 and 2. IR SENSOR. LED volume indicator. ⚡ Touch buttons: CD, LASER, TV, TUNER, PHONO, AUX 1, AUX 2, MUTE. MONITOR VCR/T 1, MONITOR VCR/T 2, VCR/T COPY: 1►2, VCR/T COPY 2►1, MONO, SPEAKER 1, SPEAKER 2. POWER: ON or OFF. HEADPHONES jack. EQUALIZER FREQUENCY controls: 30, 150, 500, 1500 and 10K. Concentric BALANCE: L to R / LOUDNESS: FLAT to MAX. ▲ VOLUME. VOLUME ▼. PANLOC buttons.



**BACK PANEL:** AUDIO OUTPUTS: SWITCHED 1, SWITCHED 2, MAIN, TAPE 3, VCR 2/TAPE 2, VCR 1/TAPE 1. EXTERNAL PROCESSORS: MAIN: TO and FROM. TAPE: TO and FROM. AUDIO INPUTS: VCR1/TAPE 1, AUX 2, AUX 1, TUNER, TV, LASER, CD, PHONO. Ground binding post. ⚡ Power cord. AC outlets: 1 UNSWITCHED, 7 SWITCHED. AREA CONTROLLER DIN socket. speaker control relay socket. 15 pin TUNER connector. 15 pin (**MVS 3**) VIDEO SELECTOR connector. Coax EXTERNAL SENSOR connectors: 1 and 2. DIN CD controller socket. Panloc mounting.

**SPECIFICATIONS:** **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.007%. **Noise and Hum:** - 98dB aux, -90dB phono. **Output Rated:** 1.5V. **Maximum Output:** 8V. **Input Sensitivity and Impedance:** high level 0.20V (10V max) at 22k, phono 2mV (100mV max) at 47k and 65pF. **Program Equalizer:** 30, 150, 500, 1500 and 10,000Hz boost or cut 12dB. **Voltage Gain:** 17.5dB high level, 62dB phono. Has **HR031** hand remote control. **Power Requirements:** 120V at 25 Watts.

**CABINET:** **L 52** Also fits **L 11**, **L 12**, and **L 62**

# C 31V

STEREO PRE-AMPLIFIER –  
VIDEO CONTROL CENTER

McIntosh  
The Compendium



**C 31V** - Sold from June 1987 - 1989. S/N: ER1001~????? & FH1001~????? (? ,??? UNITS)

**Size:** 5-7/16"H, 16-1/8"W and 13"D behind panel. **Weight:** 16.5 lb. **\$1,895.00**