

C 33

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. LISTEN SELECTOR: AUX, TAPE 3, TAPE 2, TAPE 1, TUNER, PH 1, PH 2. MODE SELECTOR: L TO L+R, R TO L+R, STEREO Reverse, STEREO, MONO (L+R), L+R TO L and L+R TO R. EQUALIZER FREQUENCY controls: 30, 150, 500, 1500 and 10K. VOLUME. ⚡ RECORD SELECTOR: AUX, TAPE 3, TAPE 2, TAPE 1, TUNER, PH 1, PH 2. TAPE 3 INPUT and OUTPUT jacks. Pushbutton switches (with indicator lights): COMPANDOR: LISTEN or RECORD, RECORD EQUAL: IN or OUT, RECORD MONITOR: IN or OUT, FILTERS: LF: IN or OUT, HF: IN or OUT, SPEAKER/OUTPUT 1 : IN or OUT, SPEAKER/OUTPUT 2 IN or OUT, POWER: ON or OFF. 2 HEADPHONES jacks. Concentric COMPANDOR control: EXPAND, OFF or COMPRESS / RATIO control: 0 to 2. Concentric BALANCE: L to R / LOUD: FLAT to MAX. PANLOC buttons.



BACK PANEL: OUTPUTS: 2, 1, MAIN, TAPE 3, TAPE 2, TAPE 1. EXTERNAL PROCESSORS: LISTEN: TO and FROM, RECORD: TO and FROM. INPUTS: TAPE 3, TAPE 2, TAPE 1, TUNER, AUX, PHONO 2, PHONO 1. ⚡ Power cord. FUSE. TURNTABLE POWER: AUTO-MANUAL switch, 2 UNSWITCHED AC outlets (TURNTABLE POWER). 4 SWITCHED AC outlets. MONITOR AMPLIFIER: EXT INPUT, OUTPUT, LEFT and RIGHT push terminals for speaker OUTPUT. SPEAKER CONTROL RELAY socket. GROUND binding post. Panloc mounting.



TOP PANEL: COMPANDOR controls: LEVEL MATCH, SPEED: FAST, NORM and SLOW. MONITOR AMPLIFIER controls: LEFT GAIN, RIGHT GAIN, INPUT switch: EXTERNAL, LISTEN or RECORD. AUTO-ON SENSITIVITY: MIN to MAX.

CABINET: **L 52** Also fits **L 11**, **L 12**, and **L 62**

C 33

STEREO PRE-AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.01%. **Noise and Hum:** - 100dB auxiliary, -90dB phono. **Output Rated:** 2.5V. **Maximum Output:** 10V. **Input Sensitivity and Impedance:** auxiliary 0.25V (10V max) at 50k, phono 2mV (100mV max) at 47k and 65pF. **Program Equalizer:** 30, 150, 500, 1500 and 10,000Hz boost or cut 12dB. **LF Filter:** 50Hz at 12dB/octave. **HF Filter:** 7kHz at 12dB/octave. **Voltage Gain:** 20dB auxiliary, 62dB phono. **Compressor Ratios:** from 1:2 compress to 2:1 expand. **Monitor Amplifier:** 20W/ch into 8 ohms. **Distortion:** 0.01%. **Response:** 20-20kHz (+0 -0.2dB). **Sensitivity:** 0.75V. **Input Impedance:** 27k. signal to noise A weighted 100dB. **Power Requirements:** 120V at 85 Watts.



C 33 - Sold from December 1981 - March 1986. S/N: CX1001~CX4902 (3,901 UNITS)

Size: 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 26 lb. **\$2,450.00**