

C 35

STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature and anodized black aluminum panel. Indicator lights: CD, LASER, TV, TUNER, PHONO, AUX 1, AUX 2. VCR/T 1 and VCR/T 2, 1▶2, 2▶1, MONO, SPEAKER: 1 and 2. IR SENSOR. Digital % VOLUME indicator. ⚡ Touch buttons: CD, LASER, TV, TUNER, PHONO, AUX 1, AUX 2, MUTE. MONITOR VCR/T 1, MONITOR VCR/T 2, VCR/T COPY 1▶2, VCR/T COPY 2▶1, MONO, SPEAKER 1, SPEAKER 2. POWER: ON or OFF. HEADPHONES jack. EQUALIZER FREQUENCY controls: 30, 150, 500, 1500 and 10k. Concentric BALANCE: L to R / LOUDNESS: FLAT to MAX. ▲ VOLUME. VOLUME ▼. PANLOC buttons.



BACK PANEL: AUDIO OUTPUTS: SWITCHED 1, SWITCHED 2, MAIN, VCR 1/TAPE 1, VCR 2/TAPE 2. EXTERNAL PROCESSORS: MAIN: TO and FROM. TAPE: TO and FROM. AUDIO INPUTS: VCR1/TAPE 1, AUX 2, AUX 1, TUNER, TV, LASER, CD, PHONO. Ground binding post. ⚡ LEFT and RIGHT BALANCED OUTPUTS. Power cord. AC outlets: 1 UNSWITCHED, 4 SWITCHED. DIN AREA CONTROLLER socket. speaker control relay socket. 15 pin TUNER connector. 15 pin (**MVS 3**) VIDEO SELECTOR connector. Coax EXTERNAL SENSOR connectors: 1 and 2. DIN CD controller socket. Panloc mounting.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.002%. **Noise and Hum:** -105dB aux, -90dB phono. **Output Rated:** 2.5V. **Maximum Output:** 8V. **Input Sensitivity and Impedance:** high level 0.25V (10V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF. **Program Equalizer:** 30, 150, 500, 1500 and 10,000Hz boost or cut 12dB. **Voltage Gain:** 20dB high level, 60dB phono. **Power Requirements:** 120V at 25 Watts. Has **HR 35** hand remote control.

CABINET: **L 52** Also fits **L 11**, **L 12**, and **L 62**

C 35

STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh
The Compendium

PANLOC BRACKETS: Right – **003-508** / Left – **003-509**



C 35 - Sold from June 1989 - 1992. S/N: FN1001~FN????

Size: 5-7/16"H, 16-1/8"W and 13"D behind panel. **Weight:** 18 lb. **\$1,995.00**