

C 38

STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. BASS. TREBLE. RECORD SELECTOR: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. LISTEN SELECTOR: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. VOLUME. Concentric BALANCE: L to R / LOUDNESS: FLAT to MAX. ⚡ Touch buttons (with indicator lights): RECORD LOCK, MONO, MUTE. HEADPHONES jack. SPEAKERS 1, SPEAKERS 2, POWER.



BACK PANEL: Left and Right BALANCED OUTPUTS. LISTEN: OUTPUTS: SWITCHED: 2 and 1, MAIN and PROCESSOR: FROM and TO. RECORD: OUTPUTS: TAPE 3, TAPE 2, TAPE 1 and PROCESSOR: FROM and TO. AUDIO INPUTS: VIDEO, TAPE 3, TAPE 2, TAPE 1, TUNER, CD 2, CD 1, AUX, PH. Ground binding post. ⚡ POWER CONTROL jack. AREA B OUTPUT. DATA ports: VIDEO, TAPE 3, TAPE 2, TAPE 1, TUNER, CD 2, CD 1, AUX, HOME. 25 pin TO MULTI-ROOM CONTROLLER connector. ⚡ Power cord. AC outlets: 1 UNSWITCHED, AREA B POWER AMP, AREA A POWER AMP, 1 SWITCHED. Coax EXTERNAL SENSORS: AREA A and AREA B. speaker control relay socket. 15 pin TUNER CONTROL. DIN CD 2 CONTROL connector. DIN CD 1 CONTROL connector.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.002%. **Noise and Hum:** - 105dB high level, -90dB phono. **Output Rated:** 2.5V. **Maximum Output:** 8V. **Input Sensitivity and Impedance:** high level 0.25V (10V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF. **Tone Controls:** bass and treble boost or cut 12dB. **Voltage Gain:** 20dB aux, 60dB phono. **Power Requirements:** 120V at 25 Watts. Has **HR038** hand remote and **HR093** replacement.

CABINET: **L 72** Also fits **L 82**

C 38

STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh
The Compendium



C 38 - Sold from 1992 - 1998. S/N: HC1001~HC????

Size: 5-3/8"H, 17-1/2"W, 17"D behind panel. **Weight:** 20 lb. **\$2,500.00**