

C 41

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. RECORD switch: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, T3/DVD, VIDEO. LISTEN switch: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, T3/DVD, VIDEO. ⚡ BASS. TREBLE. IR sensor. BALANCE: L to R. VOLUME. ⚡ Touch buttons (with indicator lights): RECORD PROCESSOR, RECORD PROCESSOR, LOUD, MONO. HEADPHONES jack. Touch buttons (with indicator lights): MUTE, OUTPUT 1, OUTPUT 2, STANDBY/ON. POWER: ON or OFF.



BACK PANEL: POWER CONTROL jacks: MAIN, Accessory, amplifier 1 and amplifier 2. DATA PORTS: PH/AUX, VIDEO, TUNER, T3/DVD, CD 2, CD 1, TAPE 1, TAPE 2. Left and Right BALANCED MAIN OUTPUTS. Left and Right BALANCED CD1 INPUTS. ⚡ Power cord receptacle. Coax EXTERNAL SENSOR connector. LISTEN: OUTPUTS: MAIN, 2, 1 and PROCESSOR: FROM and TO. RECORD OUTPUTS: TAPE 3, TAPE 2, TAPE 1 and PROCESSOR: FROM and TO. Audio INPUTS: VIDEO, T3/DVD, TAPE 2, TAPE 1, TUNER, CD 1, PH/AUX. Ground binding post. Switch: AUX 1 or PHONO.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.002%. **Noise and Hum:** -103dB high level, -90dB phono. **Output Impedance:** 250 ohms. **Input Sensitivity and Impedance:** high level 0.25V (10V max) and 22k, phono 2.5mV (90mV max) at 47k and 65pF. **Tone Controls:** bass and treble boost and cut 12dB. Electromagnetically switched inputs. **Power Requirements:** 120V at 20 Watts. Has **HR033** hand remote and **HR093** replacement.

C 41

STEREO PRE-AMPLIFIER

McIntosh
The Compendium



C 41 - Sold from 2000 - 2003. S/N: RZ1001~ RZ????

Size: 5-3/8"H, 17-1/2"W and 17-1/2"D behind panel. **Weight:** 20.6 lb. **\$2,600.00**