

CR 16

AUDIO / VIDEO MULTIZONE CONTROL SYSTEM

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. POWER: ON or OFF. ⚡
Touch buttons: ACCESSORY CONTROL OFF, ZONE 1 to 4: SELECT PROGRAM. ZONE 1 to 4: source indicators for CD, TUNER, TAPE, AUX, TV, LV, VCR, DVD. Touch buttons (with indicators): ZONE 1 to 4: ZONE ON/OFF, ACCESSORY power ON, TRANSPORT PLAY. ⚡
Touch buttons: SYSTEM OFF, RESET, MUTE (with indicator), sources: CD, TUNER, TAPE, AUX, TV, LV, VCR, DVD. Digital VOLUME readout. IR sensor. POWER indicator light. ▼
VOLUME, VOLUME ▲.



BACK PANEL: 4 zone sections. Each has the following: [KEYPAD connector: 1 to 5. Coax EXT SENSOR. Composite VIDEO OUT to MON. ZONE AUX IN: VIDEO, DATA, Left and Right AUDIO INPUT. ⚡ BALANCED OUTPUT. BALANCED switch: FIXED or VARIABLE. Left and Right UNBALANCED OUTPUT. BASS, TREBLE and LEVEL controls.] ⚡ DIN CONTROL CONNECTORS: POWER CONTROL, MULTI-CHANNEL AMP power only. 25 pin MULTI-CHANNEL AMP connector. POWER CONTROL output. DVD, VCR 1, LV, TV, AUX, TAPE 1, TUNER, CD 2, SUM, HOME. 15 pin CONTROLLER connector. RS232 POWER connector. ⚡ Power cord connector. Composite VIDEO INPUTS: DVD, VCR 1, LV, TV / VIDEO OUTPUTS: DVD, VCR 1, LV, TV. AUDIO INPUTS: DVD, VCR 1, LV, TV, AUX, TAPE 1, TUNER, CD 2. 37 pin CONTROLLER INPUT B connector. 37 pin TO NEXT CONTROLLER connector.

CR 16

AUDIO / VIDEO MULTIZONE CONTROL SYSTEM

McIntosh

The Compendium

SPECIFICATIONS: **Frequency Response:** 20-20kHz (+0 -0.5dB). **Output:** 1. 5V (6V max). **Sensitivity:** 0.25V (6V max) all inputs. **Output Impedance:** 600 ohms. **Distortion:** 0.01%. **Signal to Noise Ratio:** -90dBA. **Gain:** variable outputs 14dB; fixed (balanced outputs) 0dB. **Tone Controls:** bass and treble 12dB boost or cut. **Power Requirements:** 120 Volts at 25 watts. Has hand held **HR042** remote control and **HR093** replacement.



CR 16 - Sold from 2000 - ? . S/N: SN1001~SN????

Size: 7-1/16"H, 17-1/2"W and 20"D. **Weight:** 27.2 pounds.

\$3,300.00