

FRONT PANEL: Glass with illuminated teal/gold nomenclature. Indicators: STEREO, LOCK and FILTER. Touch buttons with indicators: PRESETS: 1, 2, 3 and 4. Digital frequency readout. LED column for SIGNAL STRENGTH. Touch buttons: AUTO SCAN UP and AUTO SCAN DOWN. Tuning control. 

SELECTIVITY switch: NARROW OF SUPER NARROW. FILTER switch: OUT, AUTO OF IN. MODE switch: STEREO OF MONO. HEADPHONES jack. SCAN control: SLOW to FAST. MUTING control: MIN to MAX. VOLUME with on-OFF switch. PANLOC buttons.



BACK PANEL: RFINPUTS: 75 Ω CABLE and ANTENNA coax inputs. Push terminals for GND and 300 Ω ANTENNA. REMOTE control SCAN: CONTROL SIGNAL jack. STATIONS switch: PRESET OF ALL. 
Power cord. UNSWITCHED AC outlet. FUSE. SCOPE outputs: VERT (TP1) and HORIZ (TP2). Audio OUTPUTS: Left & Right 2.5V VARIABLE and 1V FIXED. Panloc mounting.



**TOP PANEL:** 4 STATION PRESETS, PRESELECT switch: IN or OUT. INPUT switch: CABLE or ANTENNA, LOCK switch: OFF or ON. DE-EMPHASIS switch: 75US, 50US, 25US, or OUT. SIGNAL STRENGTH adjustment.

FM SECTION: Sensitivity: 9.3dBF or 1.6uV for 30dB of quieting. Stereo 50dB Quieting Sensitivity: 14.7dBF or 2.5uV for 3% noise and distortion. Response: 20-15kHz (+1 -1dB). Distortion: 0.2% in stereo. Capture Ratio: 1.5. Image Rejection: 90dB. S/N: 75dB. Alternate Channel Selectivity: 90dB (narrow) and 110dB (super narrow). (continued...)

The Compendium

**Adjacent Channel Selectivity:** 8dB (narrow) and 60dB (super narrow). **Separation:** 50dB@1kHz. **Spurious Rejection:** 110dB. **SCA Rejection:** 60dB.

Power Requirements: 120V at 35 Watts.

**CABINET:** L **52** Also fits L **11**, L **12**, and L **62** 

**PANLOC BRACKETS:** Right - 0??-??? / Left - 0??-???











MR 80 - Sold from November 1979 - May 1986. S/N: CK1001~CK3818 (2,817 UNITS)

**Size:** 5-7/16"H, 16"W and 13"D from front panel. **Weight:** 28 lb. **\$2,499.00**