

MCD 500

SINGLE DISC SACD/CD PLAYER

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. TRACK ⏪ BACK / NEXT ⏩ control. IR remote sensor. Disc tray. Digital display for volume output level. LEVEL control. ⚡ 1/4" HEADPHONES jack. Touch buttons: MUTE (with indicator), INPUT selector (with indicator), SACD/CD selector, TIME indicator selector. Digital display. Touch buttons: ■ STOP (with indicator), II PAUSE (with indicator), ▶ PLAY (with indicator), OPEN/CLOSE, STANDBY/ON (with indicator).



BACK PANEL: DIGITAL AUDIO INPUTS: COAXIAL and OPTICAL. DIGITAL AUDIO OUTPUTS: COAXIAL and OPTICAL. Power cord receptacle. ⚡ FIXED L & R AUDIO OUTPUTS: UNBALANCED and BALANCED. VARIABLE L & R AUDIO OUTPUTS: UNBALANCED and BALANCED. IR: sensor input. DATA control IN. POWER CONTROL: OUT and IN.

SPECIFICATIONS: Response: 4-40kHz +0.5 -2dB (SACD); 4-20kHz +0.05 - .05dB (CD). **Dynamic Range:** better than 100dB. **Signal to Noise Ratio:** better than 110dBA. **Channel Separation:** better than 98dB. **Distortion:** 0.0015% (SACD and CD). **Sampling Rate:** 44.1kHz. **Fixed Analog Output:** 2.Vrms unbalanced and 4.Vrms balanced. **Variable Analog Output:** 0 - 6.0 Vrms unbalanced and 0 - 12.0 Vrms balanced. **Digital Output:** 0.5V p-p/75 ohm (coaxial); -15dBm to -21dBm (optical). **Transport:** twin beam laser. **Wavelength:** 650 nm (SACD)/790 nm (CD). **Laser Power:** CLASS IIa/CLASS I. Has **HR065** hand remote. **Power Requirements:** 120 Volts, at 35 watts.

MCD 500

SINGLE DISC SACD/CD PLAYER

McIntosh
The Compendium



MCD 500 - Sold from October 2008 - 2016. S/N: ZE1001~ZE???? (?,???? UNITS)
Size: 6"H, 17-1/2"W and 16.5"D behind panel. **Weight:** 28.2 lb. **\$6,500.00**