

MX 121

8 CHANNEL HOME THEATER PROCESSOR

McIntosh

The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. INPUT control. Digital information display. VOLUME control. ⚡ NAV controls: ◀, ▶, ▲, ▼. INPUT FORMAT indicators: FL, C, FR, SL, LFE, SR, SLB, S and SRB. Indicators: MULTIEQ XT, DYNAMIC VOLUME, DYNAMIC EQ, ANALOG SIGNAL, DIGITAL SIGNAL, HDMI SIGNAL. OUTPUT FORMAT indicators: FL, C, FR, SL, LFE, SR, SLB, S and SRB. IR remote sensor. ⚡ Touch buttons: MENU, ENTER, RETURN, PURE DIRECT, SURROUND MODE: AUTO or MANUAL. ZONE SEL, Z2: ON / OFF (with indicator), Z3: ON / OFF (with indicator), SLEEP, STATUS, STANDBY / ON (with indicator).



BACK PANEL: DATA input and output. IR input. NETWORK connector. COAX inputs: 1 and 2. Optical inputs: 1 and 2. Optical output. HDMI inputs 1 (BD), 2 (DVD), 3 (SAT), 4 (VCR), 5 (GAME), 6 (AUX1). HDMI outputs OUT 1 ARC, OUT 2. ⚡ iPod/USB connector. RS232 control connector. SETUP microphone connector. Optical input: (AUX 1). VIDEO inputs: AUX 1, BD, DVD, VCR, SAT. VIDEO outputs: MONITOR, VCR, ZONE 2. COMPONENT VIDEO: Inputs IN 1 (BD): Y, PB and PR, IN 2 (DVD): Y, PB and PR, IN 4 (VCR): Y, PB and PR and IN 3 (SAT): Y, PB and PR. COMPONENT VIDEO OUT: OUT 2/ZONE 2: Y, PB and PR and OUT 1: Y, PB and PR. ⚡ POWER CONTROL TRIGGER: 1 and 2. ANALOG AUDIO inputs: Left & Right PHONO, TUNER, BD, DVD, SAT, VCR, CDR, CD. 7.1 Channel INPUTS: FL, FR, C, SUB, SL, SR, SBL, SBR,. Left & Right UNBALANCED PRE outputs: FL, FR, C, SUB, SL, SR, SBL, SBR, SW2, HL, HR, WL, WR. Left & Right unbalanced ANALOG AUDIO outputs: VCR, CDR, ZONE 2, ZONE 3. ⚡ Ground connector. AUX 1 BALANCED inputs: Right & Left. BALANCED outputs: FR, FL, C, SW1, SW2, SR, SL, SBR, SBL. Power cord receptacle.

MX 121

8 CHANNEL HOME THEATER PROCESSOR

McIntosh

The Compendium

SPECIFICATIONS: **Response:** 20-20kHz (± 0.5 dB). **Distortion:** 0.005%. **Input Impedance:** High Level - 20K ohms balanced & unbalanced; Phono - 47k, 65pF. **Input Sensitivity:** High Level - 450mV Unbalanced; 900mV Balanced; Phono - 4.5mV. **Signal To Noise Ratio:** High Level 96DbA; Phono 86dbA below 10mV input. **Output Voltage:** 2.5Vrms unbalanced; 5Vrms balanced. **Output Impedance:** 220 ohms.

Power Requirements: 120 Volts, 50/60 Hz at 75 watts. Has hand remote **HR078**.



MX 121 - Sold from March 2012 - 2018. S/N: ABG1001~ABG???? & ACX 1001~ACX????

Size: 7-5/8"H, 17-1/2"W and 19-1/2"D. **Weight:** 30 lb. **\$6,000.00**