

MX 122

11.2 CHANNEL HOME THEATER PROCESSOR

McIntosh
The Compendium



FRONT PANEL: LED/fiber-optic illuminated green nomenclature. **INPUT** control. Digital information display. **VOLUME** control. ⚡ **NAV** controls: ◀, ▶, ▲, ▼. Indicators: DOLBY, DTS, AUDYSSEY: IN/OUT. **INPUT/OUTPUT FORMAT** indicators: FL, C, FR, SL, LFE, SR, SLB, S and SRB. Indicators: ANALOG SIGNAL, DIGITAL SIGNAL, HDMI SIGNAL, MULTIZONE. **OUTPUT FORMAT** indicators: FL, C, FR, SL, LFE, SR, SLB, S and SRB. IR remote sensor. ⚡ **Touch** buttons: RETURN, SETUP, STATUS, MOVIE, MUSIC, GAME. **Touch** buttons: ZONE SEL, Z2: ON / OFF, Z3: ON / OFF, DIMMER, SLEEP, STANDBY / ON (with indicator).



BACK PANEL: BLUETOOTH WI-FI ANTENNA. **HDMI** inputs: 1 (cable/satellite), 2 (DVD), 3 (BLU-RAY), 4 (GAME), 5 (MEDIA PLAYER), 6 (AUX), 7 (CD). **HDMI** outputs: ZONE 2, MONITOR 1, MONITOR 2. **NETWORK** connector. **USB** connector. BLUETOOTH WI-FI ANTENNA. ⚡ **DIGITAL AUDIO** inputs: COAX 1 (cable/satellite) and 2 (DVD) / **OPTICAL**: (TV AUDIO) and 2 (CD). **RS232** control connector / **SETUP** microphone connector. **TRIGGER 1** / **TRIGGER 2**. **IR** input / **DATA** output. **XLR BALANCED INPUT**: Right & Left. **VIDEO**: 1 (cable/satellite) / 2 (DVD), 3 (Blu-Ray) / 4 (GAME), (MONITOR output) / (Z2 output). **COMPONENT VIDEO**: inputs 1 (cable/satellite): Y, PB and PR / inputs 2 (DVD): Y, PB and PR, inputs 3 (BLU-RAY): Y, PB and PR, **MONITOR** output: Y, PB and PR / **ZONE 2** output: Y, PB and PR. ⚡ **GROUND** connector. **ANALOG AUDIO** inputs:

MX 122

11.2 CHANNEL HOME THEATER PROCESSOR

McIntosh

The Compendium

Left & Right PHONO, TUNER, Cable/Satellite, DVD, BLU-RAY, GAME, CD, MP. 7.1 Channel INPUTS: FL, FR, C, SUB, SL, SR, SBL, SBR. UNBALANCED PRE OUTPUTS: FL, FR, C, SUB, SL, SR, SBL, SBR, SW2, HL1, HR1, HL2, HR2, WL, WR. Left & Right unbalanced ANALOG AUDIO OUTPUTS: ZONE 2, ZONE 3. ⚡ BALANCED OUTPUTS: FR, FL, C, SW, SW2, SR, SL, SBR, SBL, HR1, HL1, HR2, HL2. Power cord receptacle.

SPECIFICATIONS: *Frequency Response:* 20-20kHz (± 0.5 dB). *Total Harmonic Distortion:* 0.005%. *Output Voltage:* 2.5Vrms Unbalanced; 5Vrms Balanced. *Input Impedance:* High Level - 20K ohms balanced & unbalanced; Phono - 47k, 65pF. *Input Sensitivity:* High Level - 450mV Unbalanced; 900mV Balanced; Phono - 4.5mV. *Signal To Noise Ratio:* High Level 96dBA; Phono 86dBA below 10mV input. *Output Impedance:* 220 ohms. *Inputs:* 9 Analog Stereo (8 unbalanced + 1 balanced), 7 HDMI, 4 Composite, 3 Component, 2 Optical, 2 Coax, 1 Multi-channel 7.1 (unbalanced). *Outputs:* 13 Balanced (configured for 11.2), 15 Unbalanced (configured for 11.2), 3 HDMI, 2 Component (1 for zone B), 2 Composite (1 for Zone B), 2 Stereo (unbalanced for zones B & C). *Audio Processing:* Dolby Atmos, TrueHD plus, legacy formats; **DTS** DTS-X (with upgrade, HD Master Audio plus legacy formats; **Auro 3D**, Auro-Matic 9.1, 10.1, 11.1 (with upgrade). *Video Processing:* 4K Ultra HD native sources, upconverting lower resolutions to 4K Ultra HD. *Control:* **HR088** Remote control (included), network, RS232.

Power Requirements: 120 Volts, 50/60 Hz at 75 watts.



MX 122 - Sold from 2016 - 2021. S/N: AEJ1001~AEJ????

Size: 7-5/8"H, 17-1/2"W and 19-1/2"D. **Weight:** 31 lb. **\$7,000.00**