

# MA 7000

## STEREO INTEGRATED AMPLIFIER

# McIntosh

## The Compendium



**FRONT PANEL:** Glass with LED/fiber-optic illuminated green/gold nomenclature. Left POWER OUTPUT meter (LINEAR WATTS or DECIBELS). Left and right POWER GUARD lights. Right POWER OUTPUT meter (LINEAR WATTS or DECIBELS). ⚡ BALANCE. Equalizer frequency controls: 30, 150, 500, 1500, 10k. VOLUME. ⚡ IR sensor. Pushbutton switches with indicators: CD 1, CD 2, DVD, SERVER, rec, TUNER, 1/4" HEADPHONES jack, VIDEO, PH/AUX, TAPE. Pushbutton switches: phono, MONO, OUTPUTS 1 and 2, MUTE, STANDBY/ON. POWER: ON or OFF.



**BACK PANEL:** Right speaker OUTPUT connectors for 2, 4 and 8 OHMS. Balanced CD 1 and DVD INPUTS. Left speaker OUTPUT connectors for 2, 4 and 8 OHMS. ⚡ Power cord receptacle. FUSE. POWER CONTROL connectors: MAIN, Accessory, POWER CONTROL 1 and 2. Coax EXTERNAL SENSOR connector. DATA PORTS: CD1, SERVER, CD 2, REC, DVD, TUNER. Input: PHONO. Ground binding post. Inputs: CD 2, SERVER, REC, TUNER, Jumper: POWER AMP inputs. OUTPUTS: POWER AMP OUTPUTS 1, REC, balanced OUTPUTS 2.

**SPECIFICATIONS:** 250w/ch. **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.005%. **Output Impedance:** 2, 4 and 8 ohms. **Dynamic Headroom:** 2.0dB. **Noise and Hum:** 115dB power amp, -100dB high level, -84dB low level re 5mV. **Damping Factor:** >40. **Input Sensitivity and Impedance:** high level 0.25V (8V max unbalanced) at 20k, phono 2.5mV (45mV max) at 47k and 65pF. **Equalizer Controls:** boost or cut 12dB at 30 Hz, 150 Hz, 500 Hz, 1500 Hz. Power Guard. Sentry Monitor. **Autoformers.** **Power Requirements:** 120V at 6.6 Amps. Has hand remote **HR058** and **HR093** replacement.

# MA 7000

## STEREO INTEGRATED AMPLIFIER

McIntosh  
The Compendium



**MA 7000** - Sold from 2008 - 2016. S/N: ZY1001~ZY????

**Size:** 9-7/16"H, 17-1/2"W and 22"D. **Weight:** 97.5 lbs. **\$7,000.00**