

# MC275 CE

## STEREO POWER AMPLIFIER

McIntosh  
The Compendium



**CONTROLS & CONNECTORS:** Chrome/black chassis. LEFT and RIGHT speaker OUTPUT barrier strips for 4, 8 and 16 OHMS. Left and Right (MONO) audio XLR BALANCED INPUTS jacks. Left and Right (MONO) UNBALANCED GAIN controls: 2.5V to 1.0V. ⚡ Power cord. AC outlet. FUSE. MODE switch: MONO or STEREO. INPUT switch: BALANCED or UNBALANCED. Left and Right (MONO) audio UNBALANCED INPUTS.



**SPECIFICATIONS:** 75w/ch stereo, 150w mono. **Response:** 20-20kHz (+0 -0.2dB). **Distortion:** 0.5%. **Noise & Hum:** -100dB (A weighted). **Output Impedance:** 4, 8, 16 ohms. (2, 4, and 8 ohms in mono). 25V line. **Damping Factor:** greater than 10. **Input Impedance:** 100k unbalanced, 180k balanced. **Input Sensitivity:** 1.0V unbalanced, 2.0V balanced. *Unity Coupled.* **Power Requirements:** 120V at 400 Watts.

**TUBES:** 4-KT88/6550 output, 3-12AX7A, 4-12AZ7. Solid state rectifier bridge.

# MC275 CE

## STEREO POWER AMPLIFIER

McIntosh  
The Compendium



**MC275 CE features:** 1. Hybrid PCB/Point-to-point wiring. 2. Chrome chassis. 3. 450 v power supply.

**MC275 CE "Spotting features":** 1. Side **Gordon Gow Commemorative Edition** badge. 2. Gain controls. 3. Unbalanced inputs on far right-hand side of the vertical front. 4. Power cord and fuse are on the vertical front. 5. Convenience outlet on vertical front panel. 6. Terminal strips are horizontal.

**MC275 CE** - Sold from 1993 - 1998. S/N: E1001?~E???? (? , ??? UNITS)

**Size:** 7-1/2"H, 12"W and 16"D. **Weight:** 67 lb. **\$4,000.00**