

# MC275 [MK V]

## STEREO POWER AMPLIFIER

**McIntosh**  
The Compendium



**CONTROLS & CONNECTORS:** Polished stainless steel/black chassis. LEFT speaker OUTPUT binding posts: COM, 4  $\Omega$ , 8  $\Omega$ , 16  $\Omega$ . RIGHT speaker OUTPUT binding posts: COM, 4  $\Omega$ , 8  $\Omega$ , 16  $\Omega$ . (Early binding posts were plastic - later were gold-plated metal.) MODE switch: MONO or STEREO. Left and Right/ MONO audio XLR BALANCED INPUTS jacks. INPUTS switch: BALANCED or UNBALANCED. Left and Right/MONO audio UNBALANCED INPUTS. ⚡ POWER switch OFF or ON.



EARLY



LATE

# MC275 [MK V]

## STEREO POWER AMPLIFIER

**McIntosh**  
The Compendium

**SPECIFICATIONS:** 75w/ch stereo into 4, 8 or 16 ohms, 150w mono into 2, 4, or 8 ohms. **Response:** 20-20kHz (+0 -0.5dB), 20-70kHz (+0,-3dB). **Distortion:** 0.5%. **Noise & Hum:** -100dB (A weighted). **Output Impedance:** 4, 8, 16 ohms. (2, 4, and 8 ohms in mono). **Damping Factor:** greater than 14. **Input Impedance:** 90k unbalanced, 180k balanced. **Input Sensitivity:** 1.2V unbalanced, 2.5V balanced. *Unity Coupled.* **Power Requirements:** 120V at 12 Amps.

**TUBES:** 4-KT88/6550 output, 3-12AX7A, 4-12AT7. Solid state rectifier bridge.



**MC275 [MK V] features:** 1. PCB wiring. 2. Stainless steel chassis. 3. 450 v power supply. 4. RoHS.

**MC275 [MK V] "Spotting features":** 1. No gain controls. 3. Unbalanced inputs on far right-hand side of the slanted front panel. 4. 5-way speaker binding posts. 5. Power cord socket and fuse are on the rear panel.

**MC275 [MK V] - Sold from 2009 - 2012. S/N: WM1001~WM????**

**Size:** 8-1/4"H, 12"W and 16-1/2"D. **Weight:** 67 lb. **\$3,500.00**