

# MC 602

## STEREO POWER AMPLIFIER

McIntosh  
The Compendium



**FRONT PANEL:** Glass with illuminated green/gold nomenclature. Illuminated **left and right POWER OUTPUT** meters (linear **WATTS** or **DECIBELS**). **Left and right POWER GUARD** lights. ⚡ **METER** switch: **LIGHTS OFF**, **WATTS** or **HOLD**. Remote **ON** indicator light. **POWER** switch: **OFF**, **REMOTE** or **ON**.



**BACK PANEL:** POWER CONTROL jacks: OUT and IN. LEFT and RIGHT BALANCED INPUTS. LEFT and RIGHT UNBALANCED INPUTS. INPUT MODE switch: BALANCED or UNBALANCED. ⚡ Polished stainless steel chassis. CIRCUIT BREAKER. Gold plated RIGHT channel OUTPUT terminals for 2, 4, or 8  $\Omega$  speakers. Gold plated LEFT channel OUTPUT terminals for 2, 4, or 8  $\Omega$  speakers. Power cord receptacle.

# MC 602

## STEREO POWER AMPLIFIER

# McIntosh

## The Compendium

**SPECIFICATIONS:** 600w/ch into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Signal to Noise Ratio:** -124dBA balanced, -120dBA unbalanced. **Output Impedance:** 2, 4, or 8 ohms. **Damping Factor:** 100 at 8 ohms. **Input Impedance:** 10K balanced and 20K unbalanced. **Input Sensitivity:** 4.9v balanced and 2.45v unbalanced. **Dynamic Headroom:** 2.1 dB. Sentry Monitor. Power Guard. **Autoformers.** Power requirements 120V at 15 Amps.



**MC 602** - Sold from 2003 - 2007. S/N: RX1001~RX????

**Size:** 11"H, 17-3/4"W and 19.63"D. **Weight:** 155 lbs.

**\$8,100.00**