

MC 7106

SIX CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Power indicator light. ⚡ Channel ONE and TWO POWER GUARD lights. Channel THREE and FOUR POWER GUARD lights. Channel FIVE and SIX POWER GUARD lights. ⚡ Six LED POWER LEVEL columns in X10 increments from .01W to 100W for each channel.



BACK PANEL: POWER switch: ON or OFF/REMOTE. FUSE. Power cord. [Channels 6 and 5 section: INPUTS: 6 and 5 / BRIDGED. 6 and 5 / BRIDGED LEVEL controls: 2.5V to 1.0V THX. MODE switch: NORMAL or BRIDGED. Speaker OUTPUTS terminals: 6 and 5]. DISPLAY BRIGHTNESS control: MAXIMUM to OFF. POWER CONTROL jacks: IN and OUT. [Channels 4 and 3 section: INPUTS: 4 and 3 / BRIDGED. 4 and 3 / BRIDGED LEVEL controls: 2.5V to 1.0V THX. MODE switch: NORMAL or BRIDGED. Speaker OUTPUTS terminals: 4 and 3]. THX 25 pin INPUT connector. [Channels 2 and 1 section: INPUTS: 2 and 1 / BRIDGED. 2 and 1 / BRIDGED LEVEL controls: 2.5V to 1.0V THX. MODE switch: NORMAL or BRIDGED. Speaker OUTPUTS terminals: 2 and 1].

SPECIFICATIONS: Six channels. **100w/ch** into 8 ohms or **160w** into 4 ohms. (**300w** into 8 ohms mono with 2 channels bridged). **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Noise and Hum:** -113dBA. **Output:** direct coupled for 4 to 8 ohms. **Damping Factor:** 100 or greater. **Input Impedance:** 20k. Input Sensitivity: 1v. Sentry Monitor. Power Guard. Direct coupled. THX approved.


CABINET: L 84 Also fits L 74

MC 7106

SIX CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



MC 7106 - Sold from 1992 - 1998. S/N: HE1001~HE????

Size: 7-1/8"H, 17-1/2"W and 20"D. **Weight:** 52 lb. **\$3,500.00**