

# MC 7108

## EIGHT CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 7, 6, 5 OR 4 CHANNELS

# McIntosh

## The Compendium



LATE

**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. 4 **POWER** indicator lights indicate when each channel pair is active. ⚡ **POWER GUARD** lights for channels **ONE**, **TWO**, **THREE**, **FOUR**, **FIVE** and **SIX**. Later **PA** serial number version had a **POWER** switch on the right side.



LATE

**BACK PANEL:** Horizontal **POWER** switch: **ON** or **OFF/REMOTE** [**KW** series]; vertical **POWER CONTROL** switch: **LOCAL** or **REMOTE** [**PA** series]. **FUSE**. Power cord [fixed on **KW** series; receptacle on **PA** series]. [Channels 8 and 7 section: Input and output: 8 and 7/**BRIDGED**. 8 and 7/**BRIDGED** **LEVEL** controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED**, **STEREO** or **MONO**. Speaker output terminals: 8 and 7.] [Channels 6 and 5 section: Input and output: 6 and 5/**BRIDGED**. 6 and 5/**BRIDGED** **LEVEL** controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED**, **STEREO** or **MONO**. Speaker output terminals: 6 and 5.] **8 CHANNEL IN** 25 pin connector. **POWER CONTROL** jacks: **IN** and **OUT**. **MULTI-ROOM** connector. [Channels 4 and 3 section: Input and output: 4 and 3/**BRIDGED**. 4 and 3/**BRIDGED** **LEVEL** controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED**, **STEREO** or **MONO**. Speaker output terminals: 4 and 3.] [Channels 2 and 1 section: Input and output: 2 and 1/**BRIDGED**. 2 and 1/**BRIDGED** **LEVEL** controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED**, **STEREO** or **MONO**. Speaker output terminals: 2 and 1.]

# MC 7108

## EIGHT CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 7, 6, 5 OR 4 CHANNELS

# McIntosh

## The Compendium

**SPECIFICATIONS:** Eight channels. **40w/ch** into 4 ohms. (**100w** into 4 ohms mono with 2 channels bridged). **Response:** 20-20kHz (+0 -0.25dB). **Distortion:** 0.005%. **Noise and Hum:** -112dBA. **Output:** direct coupled for 4 to 8 ohms. **Damping Factor:** 100 or greater. **Input Impedance:** 20k. **Input Sensitivity:** 1v. Sentry Monitor. Power Guard. Direct coupled.

**CABINET:** L 84 Also fits L 74



Early version (KW serial number)



Later version (PA serial number)



**MC 7108** - Sold from 1994 - 2000. S/N: KW 1001~KW???? & PA1001~PA????

**Size:** 7-1/16"H, 17-1/2"W and 20"D. **Weight:** 40 lb. **\$2,500.00**