

# MC 8207

## SEVEN CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



**FRONT PANEL:** LED/fiber-optic illuminated green/gold nomenclature. Three LED digital POWER OUTPUT meters (WATTS): FRONT LEFT, CENTER, and FRONT RIGHT. ⚡ 3 POWER GUARD lights – front left, center and front right. ⚡ 4 POWER GUARD lights – surround Left, surround Back Left, surround Back right, and surround right. POWER switch: ON, OFF/REMOTE.



**BACK PANEL:** Speaker OUTPUTS connectors: Front Right/channel 7, surround Right /channel 6, ⚡ center/channel 3. surround Back Left/channel 4. surround Back Right/channel 5. ⚡ Front Left/channel 1, surround Left/channel 2. ⚡ Power cord receptacle. CIRCUIT BREAKER. AUTO OFF switch: DISABLE or ENABLE. POWER CONTROL connectors: IN Z A and Z B and OUT Z A and Z B. IMPEDANCE switch: 8 Ω or 4Ω. Balanced INPUTS: channel 7/Front Right, channel 6/surround Right, channel 5/surround Back Right/ZONE B. Unbalanced ZONE B Left and Right. Balanced INPUTS: surround Back Left/channel 4/ZONE B, channel 3/center, channel 2/surround Left, channel 1/Front Left.

# MC 8207

## SEVEN CHANNEL POWER AMPLIFIER

McIntosh

The Compendium

**SPECIFICATIONS:** Seven channels. **200w/ch** into 4 or 8 ohms. **Response:** 20-20kHz. **Distortion:** 0.005%. **Signal To Noise Ratio:** -112dBA. **Output Impedance:** 4 or 8 ohms. **Damping Factor:** >70 at 4 ohms or 140 at 8 ohms. **Input Impedance:** 10k unbalanced and 20k balanced. **Input Sensitivity:** 1v w/4ohm, 1.4v w/8ohm balanced, and 2v w/4ohm, 2.8v w/8ohm balanced. **Dynamic Headroom:** 1.7 dB. *Dynamic Power Manager. Sentry Monitor. Power Guard.* Power requirements 120V at 12 Amps.



**MC 8207** - Sold from January 2012 - Current. S/N: ABJ1001~ABJ????

**Size:** 9-7/16"H, 17-1/2"W and 21"D. **Weight:** 83 lb. **\$6,000.00**