

C 220

STEREO PRE-AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. TREBLE. IR SENSOR. Digital display. VOLUME. ⚡ HEADPHONES jack. BASS. Touch buttons (with indicator lights): TONE BYPASS, MONO, RECORD MONITOR, SETUP. Touch button: MUTE. Touch buttons (with indicator lights): OUTPUT 1, OUTPUT 2. STANDBY/ON / RESET (with indicator light).



BACK PANEL: Power cord receptacle. MAIN OUTPUTS (balanced). POWER CONTROL jacks: MAIN and ACC. TRIGGER outputs: SPKR1 (A) and SPKR2 (B). Coax EXTERNAL SENSOR connector. DATA PORTS: VCR / TAPE, DVD / SAT, CD 2 / CD, SUM / TUNER. Balanced INPUTS: DVD, CD. Ground binding post. ⚡ Fuse. OUTPUTS: MAIN, 2, 1 and TAPE. Unbalanced INPUTS: TAPE/RECORD MONITOR, VCR, SAT, DVD, CD, CD2, TUNER, PHONO.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.08%. S/N ratio: -90dB high level, -80dB phono. **Output Impedance:** 250 ohms. **Input Sensitivity and Impedance:** unbalanced high level 450mV (5V max) and 22k, balanced high level 900mV (10V max) and 22k, phono 4.5mV (50mV max) at 47k and 65pF. **Tone Controls:** bass and treble boost and cut 12dB. **Tube Complement:** Phono circuitry; 2 – 12AX7A, High level circuitry; 2 – 12AX7A. Electromagnetically switched inputs. **Power Requirements:** 120V at 75 Watts. Has **HR060** hand remote control and **HR093** replacement.

C 220

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



C 220 - Sold from 2006 - 2016. S/N: WS1001~WS???? and WX1001~WX????

Size: 6"H, 17-1/2"W and 18"D behind panel. **Weight:** 21.1 lb. **\$3,300.00**