

C 2200FG

STEREO PRE-AMPLIFIER /
VIDEO CONTROL CENTER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. **INPUT.** Illuminated left and right **OUTPUT LEVEL** meters (DECIBELS). **VOLUME.** ⚡ **BASS.** **TREBLE.** Digital display. **METER LIGHTS:** ON or OFF / **SETUP.** **BALANCE:** L to R. ⚡ **IR SENSOR.** Touch buttons: **TONE BYPASS, MONO, RECORD MONITOR, SETUP.** **HEADPHONES** jack. Touch buttons: **MUTE,** (with indicators): **OUTPUTS 1, OUTPUTS 2, STANDBY/ON.** **POWER** switch: ON or OFF.



BACK PANEL: Left and Right balanced **OUTPUTS:** **MAIN, 2, and 1.** Left and Right balanced **INPUTS:** **VCR, SAT, DVD and CD.** Ground binding post. ⚡ Left and Right unbalanced **OUTPUTS:** **MAIN, 2, 1 and TAPE/REC.** Unbalanced **INPUTS:** **TAPE/REC, VCR, SAT, DVD, CD, CD 2, TUNER and PH/AUX.** ⚡ Power cord receptacle. **FUSE.** **POWER CONTROL** outputs: **MAIN, ACC, 2 and 1.** **PASS THRU** power control. Coax **EXTERNAL SENSOR** connector. **DATA PORTS:** **TAPE, VCR, SAT, DVD, CD, CD 2, TUNER.**

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.08%. **Noise and Hum:** - 93dB high level, -80dB phono. **Maximum Output:** 8V unbalanced, 16V balanced. **Output Impedance:** 500 ohms balanced and 250 ohms unbalanced. **Input Sensitivity and Impedance:** high level 0.45V (2.5V max) at 22k unbalanced and 44k balanced, phono MM 4.4mV (50mV max) at 47k and 65pF. **Power Requirements:** 120V at 75 Watts. Has hand remote **HR044** and **HR093** replacement.

TUBES: 4-**12AX7A, 4-12AT7A.** Solid state rectifier bridges.

C 2200FG

STEREO PRE-AMPLIFIER /
VIDEO CONTROL CENTER

McIntosh
The Compendium



Frank Gow Commemorative version sold by Audio Classics.

C 2200FG - Sold in 2011. S/N: ABE1001~ABE1051

Size: 7-5/8"H, 17-1/2"W and 20"D behind panel. **Weight:** 26-3/4 lb.

\$5,500.00