

C 26

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. INPUT SELECTOR: AUX, TAPE 2, TAPE 1, TUNER, PHONO 1, and PHONO 2. MODE SELECTOR: L to L+R, R to L+R, STEREO REVERSE, STEREO, MONO (L+R), L+R TO L and L+R TO R. Power indicator light. VOLUME with on-OFF switch. ⚡ Pushbutton switches: MONITOR: TAPE 1 IN or OUT, TAPE 2 IN or OUT. FILTERS: LF IN or OUT, HF: IN or OUT, MAIN SPEAKER: ON or OFF, REMOTE SPEAKER: ON or OFF. HEADPHONES jack. LOUDNESS: FLAT to MAX. BALANCE: L to R. Dual concentric BASS control. Dual concentric TREBLE control. PANLOC buttons.



BACK PANEL: LEFT & RIGHT push terminals for AMPLIFIER OUTPUT, MAIN SPEAKERS and REMOTE SPEAKERS. INPUTS: AUX, TAPE 2, TAPE 1, TUNER, PH 1 and PH 2. ⚡ FUSE. Power cord. AC OUTLETS: 1 unswitched, 4 switched. OUTPUTS: L+R, MAIN (2 pair). GROUND binding post. OUTPUTS: TAPE 1 and 2. Panloc mounting.



TOP PANEL: PHASE CONTROL: 180° or 0° NORMAL. CENTER CHANNEL LEVEL: MIN. to MAX.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.1%. **Noise and Hum:** - 85dB aux, -74dB phono. **Output Rated:** 2.5v, 10v max. **Output Impedance:** 200 ohms. **Load Impedance:** 47k. **Input Sensitivity and Impedance:** aux 0.25V at 250k, phono 2mV at 47k. **Center Channel Out (L+R):** 2.5v with control (+6 -6 dB re main output). **Tone Controls:** bass +16dB to -20dB, treble +20 to -20dB. Loudness continuously variable. **LF Filter:** 50Hz at 6dB/octave. **HF Filter:** 5kHz at 6dB/octave. **Voltage Gain:** 20dB aux, 62dB phono. Switch for power amp output to main and/or remote speakers. **Power Requirements:** 120V at 15 Watts.

CABINET: **L 12** Also fits **L 11**, **L 52**, and **L 62**

C 26

STEREO PRE-AMPLIFIER

McIntosh

The Compendium

PANLOC BRACKETS: Right – **043-592** / Left – **043-593**



C 26 - Sold from April 1968 - 1978. S/N: 10P01~99P99 & AG1001~AG7398
(15,208 UNITS)

Size: 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 18 lb. **\$449.00**