

C 29

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Concentric BALANCE: L to R / LOUD: FLAT to MAX. INPUT SELECTOR (with indicator lights): AUX 1, AUX 2, TUNER, PHONO 1, and PHONO 2, MIC. MODE SELECTOR (with indicator lights): L TO L+R, R TO L+R, STEREO REVERSE, STEREO, MONO (L+R), L+R TO L and L+R TO R. VOLUME. ⚡ Dual concentric BASS control. TAPE 2 INPUT and OUTPUT jacks. Pushbutton switches (with indicator lights): MONITOR TAPE 1: IN and OUT, MONITOR TAPE 2: IN and OUT, TAPE COPY: 1→2, TAPE COPY: 2→1, FILTERS: LF: ON or OFF, HF: ON or OFF, SPEAKERS 1: ON or OFF, SPEAKERS 2: ON or OFF. POWER: ON or OFF. 2 HEADPHONES jacks. Dual concentric TREBLE control. PANLOC buttons.



BACK PANEL: 4 SWITCHED AC outlets. 2 UNSWITCHED AC outlets (TURNTABLE auto-on). TURNTABLE FUSE. AUTO-MANUAL switch. ⚡ power cord. MAIN FUSE. ⚡ INPUTS: AUX 1, AUX 2, TUNER, PH 1, PH 2, MIC, TAPE 1, TAPE 2. Ground binding post. ⚡ SPEAKER CONTROL RELAY socket. OUTPUTS: MAIN (2 pair), LINE, TAPE 1 and TAPE 2. Panloc mounting.



TOP PANEL: LEFT and RIGHT MAIN OUTPUT LEVEL. LEFT and RIGHT HEADPHONE AND LINE OUTPUT LEVEL.

CABINET: L 52 Also fits L 11, L 12, and L 62

PANLOC BRACKETS: Right - 0??-??? / Left - 0??-???

C 29

STEREO PRE-AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.02%. **Noise and Hum:** - 90db aux, -80dB phono. **Output Rated:** 2.5v. **Output Impedance:** 100 ohms. **Load Impedance:** 10k. **Input Sensitivity and Impedance:** aux 0.25V at 100k, phono 2mV at 47k and 65pF, mic 2.5mV at 10k. **Tone Controls:** bass +20dB to -20dB, treble +18 to -18dB. **Headphone Amplifier:** 0.75V at 8 ohms. **LF Filter:** 50Hz at 12dB/octave. **HF Filter:** 7kHz at 12dB/octave. **Voltage Gain:** 20dB aux, 62dB phono. **Power Requirements:** 120V at 45 Watts.



C 29 - Sold from July 1978 - 1985. S/N: BZ1001~BZ8295 (7,294 UNITS)

Size: 5-7/16"H, 16"W and 13"D behind panel. **Weight:** 21 lb. **\$1,399.00**