

C 36 (& C 36W and Export Model)

STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh
The Compendium



EARLY (NARROW FACEPLATE)



LATER (WIDE FACEPLATE)

FRONT PANEL: Glass with illuminated teal/gold nomenclature and anodized black aluminum panel. BASS. TREBLE. RECORD SELECTOR: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. LISTEN SELECTOR: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. VOLUME. Concentric BALANCE: L to R / LOUDNESS: FLAT to MAX. ⚡ HEADPHONES jack. Touch buttons (with indicator lights): MUTE, MONO, POWER, SPEAKERS: 1 & 2. PANLOC buttons.



BACK PANEL: LISTEN: OUTPUTS: SWITCHED: 2 and 1, MAIN and PROCESSOR: FROM and TO. RECORD: OUTPUTS: TAPE 3, TAPE 2, TAPE 1 and PROCESSOR: FROM and TO. AUDIO INPUTS: VIDEO, TAPE 3, TAPE 2, TAPE 1, TUNER, CD 2, CD 1, AUX, PH. ⚡ Power cord. AC outlets: 1 UNSWITCHED, 8 SWITCHED. Ground binding post. speaker control relay socket. PANLOC mounting.

C 36 (& C 36W)

**STEREO PRE-AMPLIFIER /
VIDEO CONTROL CENTER**

McIntosh
The Compendium

SPECIFICATIONS: *Response:* 20-20kHz (+0 -0.5dB). *Distortion:* 0.002%. *Noise and Hum:* - 105dB high level, -90dB phono. *Output Rated:* 2.5V. *Maximum Output:* 8V. *Input Sensitivity and Impedance:* high level 0.25V (10V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF. *Tone Controls:* bass and treble boost or cut 12dB. *Voltage Gain:* 20dB aux, 60dB phono. *Power Requirements:* 120V at 15 Watts.

CABINET: **L 52 NARROW** Also fits **L 11**, **L 12**, and **L 62** **L 72 (WIDE C 36)**

PANLOC BRACKETS: Right - **00350800** / Left - **00350900**



EARLY (NARROW FACEPLATE)



LATER (WIDE FACEPLATE)

In 1992, **McIntosh** increased the chassis and/or faceplate width of many of their products. The production cycle of the **C 36** spanned this change.

Early production units had the 16-3/16" wide faceplate. Later production units had the 17-1/2" faceplate.



EARLY

C 36 (Export Model)

STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh
The Compendium

During the course of C 36 production McIntosh also produced an export model C 36 for a variety of voltages. Early production version was identical to the early domestic C 36. Later production was in the wider chassis and this version utilized the C 38-style faceplate and included Balanced Outputs and a Power Control output. No PANLOC mounting.



C 36 EXPORT MODEL

EXPORT MODEL FRONT PANEL: Glass with illuminated teal/gold nomenclature. BASS. TREBLE. RECORD SELECTOR: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. LISTEN SELECTOR: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. VOLUME. Concentric BALANCE: L to R / LOUDNESS: FLAT to MAX. ⚡ Touch buttons (with indicator lights): Listen Processor, MONO, MUTE. HEADPHONES jack. Touch buttons (with indicator lights): SPEAKERS 1, SPEAKERS 2, POWER.



EXPORT MODEL BACK PANEL: Left and Right BALANCED OUTPUTS. LISTEN: OUTPUTS: SWITCHED: 2 and 1, MAIN and PROCESSOR: FROM and TO. RECORD: OUTPUTS: TAPE 3, TAPE 2, TAPE 1 and PROCESSOR: FROM and TO. AUDIO INPUTS: VIDEO, TAPE 3, TAPE 2, TAPE 1, TUNER, CD 2, CD 1, AUX, PH. Ground binding post. ⚡ Power cord. AC outlets: 1 UNSWITCHED, 8 SWITCHED. POWER CONTROL jack. speaker control relay socket.

C 36 - Sold from 1992 – 1994. S/N: GV1001~GV????

Early export model S/N: GR1001~GR?????. Later export model S/N: JK1001~JK????

Size: 5-7/16"H, [Front panel width was 16-1/8" in early units (**C 36**) and 17-1/2" in later units (**C 36W**)], 15-1/2"D behind panel. **Weight:** 14.5 lb. **\$1,700.00**