

# C 46

## STEREO PRE-AMPLIFIER / VIDEO CONTROL CENTER

McIntosh  
The Compendium



**FRONT PANEL:** Glass with LED/fiber-optic illuminated green/gold nomenclature. **BALANCE:** L to R / MENU. **RECORD.** Digital display. **LISTEN.** **VOLUME.** ⚡ **EQUALIZER FREQUENCY** controls: 20, 35, 70, 150, 300, 600, 1.2k and 4k. ⚡ Touch buttons: **RECORD PROCESSOR**, **Listen PROCESSOR**, **Record MONITOR**, **MONO**, **SETUP**. **HEADPHONES** jack. Touch buttons: **TONE BYPASS**, **MUTE**, **OUTPUTS 1**, **OUTPUTS 2**. **IR** sensor. Touch buttons: **STANDBY/ON** (with indicator). **POWER:** ON or OFF.



**BACK PANEL:** **POWER CONTROL** jacks: MAIN, ACC, amplifier 1 and amplifier 2. **DATA PORTS:** VCR / TAPE, DVD / SAT, CD / CD 2, PH/AUX / TUNER. Left and right **BALANCED OUTPUTS:** MAIN, 2 and 1. Left and right **BALANCED CD INPUTS.** ⚡ **Power cord** receptacle. **FUSE.** Coax **EXTERNAL SENSOR** connector. **LISTEN:** MAIN, 1 and 2, **PROCESSOR:** FROM and TO. **RECORD:** TAPE and VCR, **PROCESSOR:** FROM and TO. **INPUTS:** TAPE, VCR, SAT, DVD, CD 2 TUNER, AUX. Ground binding post. **Phono** inputs. Switch: AUX or PHONO.

**SPECIFICATIONS:** **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.002%. **Noise and Hum:** - 97dB aux, -86dB phono. **Output Rated:** 2.5V unbalanced and 5.0V balanced. **Maximum Output:** 10V unbalanced and 20V balanced. **Input Sensitivity and Impedance:** high level 0.45V (5V max) at 22k unbalanced and 0.90V (10V max) at 50k balanced, phono 4.5mV (50mV max) at 47k and 65pF. **Tone Controls:** bass and treble boost and cut 12dB. **Voltage Gain:** 15dB high level, 40dB phono. **Power Requirements:** 120V at 50 Watts. Has hand remote **HR044** and **HR093** replacement.

# C 46

STEREO PRE-AMPLIFIER /  
VIDEO CONTROL CENTER

McIntosh  
The Compendium



**C 46** - Sold from 2002 - 2010. S/N: XE1001~XE???? and UG1001~UG????

**Size:** 5-3/8"H, 17-1/2"W and 19"D behind panel. **Weight:** 26 lb.

**\$3,500.00**