


MAC 1900

AM-FM STEREO RECEIVER

McIntosh
The Compendium



FRONT PANEL: Gold and black anodized aluminum panel. Illuminated tuning dial. Indicator lights: FM MPX, TAPE 1, TAPE 2, AM, FM, PH 1, PH 2, TAPE MON. Meters: TUNING and SIGNAL STRENGTH. Tuning control. ⚡ INPUT SELECTOR: TAPE 1, TAPE 2, AM, FM, PH 1, PH 2. HEADPHONES jack. Pushbutton switches: STEREO, STEREO REVERSE, MONO, L TO L&R, R TO L&R, L+R TO L, L+R TO R, LOUD, MONITOR: TAPE 1 and TAPE 2, FILTERS: LF and HF, MUTING, SPEAKERS: MAIN, REMOTE 1, REMOTE 2. Slide type BASS and TREBLE controls with center detent. BALANCE. VOLUME with on-OFF switch.



EARLY



LATE

BACK PANEL: LEFT and RIGHT output push terminals for MAIN SPEAKERS, REMOTE SPEAKERS 1 and REMOTE SPEAKERS 2. Built-in ferrite AM loopstick. ⚡ FUSE. Power cord. AC OUTLETS: 1 UNSWITCHED, 2 SWITCHED. Scope outputs: TP 1 and TP 2. GROUND terminal. Push terminals for: AM ANTENNA, GROUND. 300 Ω FM ANTENNA. 75 Ω FM ANTENNA coax input. Jumpers: AMP INPUT and PREAMP OUT. TAPE OUT 1. TAPE OUT 2. INPUTS: TAPE MON 1, TAPE MON 2, PH 1. Ground screw terminal. PH 2 INPUT. (Late units had a LOAD IMPEDANCE switch: [some had 8-16 Ω or 4 Ω, some had 8 Ω or 4 Ω] between the power cord and unswitched outlet. Early cover had round holes. Late cover had slots.)

AM SECTION: **Sensitivity:** 75uV IHF. **S/N:** 45dB IHF. **Distortion:** 1%, **Response:** 20-3500Hz @ -6Db. **Image Rejection:** 65dB. **Adjacent Channel Selectivity:** 30dB.

FM SECTION: **Sensitivity:** 2.5uV. **S/N:** 70dB IHF. **Distortion:** 0.7% in stereo. **Response:** 20-15kHz (+1.0 -1.0dB). **Capture Ratio:** 1.8dB. **Selectivity:** 55dB IHF. **Spurious Rejection:** 90dB IHF. **Image Rejection:** 80dB IHF. **Stereo Separation:** 34dB. **SCA Rejection:** 50dB.



MAC 1900

AM-FM STEREO RECEIVER

McIntosh

The Compendium

SPECIFICATIONS: 55w/ch into 4 or 8 ohms. **Response:** 20-20kHz (+0.5 -0.5dB).
Distortion: .2%. **Noise and Hum:** power amp -95dB, aux -90dB, phono -76dB.
Damping Factor: 50. **Input Impedance:** power amp 100k, aux 250k, phono 47k.
Input Sensitivity: power amp 2.5V, aux 0.25V, phono 2.0mV. **Tone Controls:**
bass and treble. +16 to -16dB. **LF Filter:** 50Hz at 12dB/octave. **HF Filter:** 7kHz at
12dB/octave. **Direct coupled.** **Power Requirements:** 120V at 300 Watts.

CABINET: L 19WVO



MAC 1900 - Sold from 1973 - 1979. S/N: 1X001~9X999, AL1001~AL2205 &
AN1020~AN4201 (13,383 UNITS)

Size: 5-1/2"H, 16"W and 15"D. **Weight:** 33 lb. Last retail price **\$949.00**