

# CR 8

## REMOTE AREA CONTROLLER

McIntosh

The Compendium



**FRONT PANEL:** Black anodized aluminum panel. **POWER** indicator light.



**BACK PANEL:** Left and Right **OUTPUT**. ⚡ Power cord. AC outlets: 1 **UNSWITCHED**, 1 **POWER AMP**. Coax **AREA SENSOR** connector. 25 pin **TO NEXT AREA CONTROLLER** output connector. 25 pin **AREA CONTROLLER INPUT** connector.

**SPECIFICATIONS:** **Frequency Response:** 20-20k (+0 -0.5). **Output:** 2.5V (5V max). Sensitivity: 0.775V (5V max) all inputs. **Distortion:** 0.007%. **Signal to Noise Ratio:** -84dBA IHF. **Input Impedance:** 100k. **Power Requirements:** 120 Volts at 8 watts. Has **HR7** hand remote.



**CR 8** - Sold from September 1986 - 1991. S/N: EM1001~EM????

**Size:** 3-1/16"H, 8-3/16"W and 9-1/2"D. **Weight:** 6 lb. **\$678.00**