



EARLY

(EARLY) FRONT PANEL: Glass with illuminated teal/gold nomenclature. Touch button keypad for 50 presets: 1 through 9 and 0. LED SIGNAL strength bar. Indicator lights: AM, FM and MPX. Digital frequency and PRESET readout. Mode indicator lights: ENTER, REVIEW, SPATIAL. Touch buttons: ▲ TUNE, AM, SPATIAL, REVIEW. ▼ TUNE, FM, ENTER. POWER: ON (with indicator) or OFF.



LATE

(LATE) FRONT PANEL: Glass with illuminated teal/gold nomenclature. Touch button keypad for 50 presets: 1 through 9 and 0. LED SIGNAL strength bar. Indicator lights: AM, FM and MPX. Digital frequency and PRESET readout. Mode indicator lights: ENTER, REVIEW, SPATIAL. Touch buttons: ▲ TUNE, AM/FM, SPATIAL. ▼ TUNE, REVIEW, ENTER. POWER: ON (with indicator) or OFF.



(EARLY) BACK PANEL: Power cord. PRESET CLEAR button. DATA IN/OUT jacks for remote. SCOPE outputs: H and V. Left & Right audio OUTPUT: FIXED and VARIABLE. OUTPUT LEVEL adjustment. 75 Ω FM ANTenna coax input. External AM ANTenna input. Built-in AM ferrite loopstick.



(LATE) BACK PANEL: Power cord receptacle. PRESET CLEAR button. DATA IN/OUT jacks for remote. POWER IN and OUT jacks. SCOPE outputs: H and V. Left & Right audio OUTPUT: FIXED and VARIABLE. OUTPUT LEVEL adjustment. 75 Ω FM ANTenna coax input. External AM ANTenna input. Built-in AM ferrite loopstick.

FM SECTION: Sensitivity: 15dBF or 1.6uV across 75 ohms. Stereo 50dB Quieting Sensitivity: 39dBF or 25uV across 75 ohms. Response: 20-15kHz (+0 -1dB). Distortion: 0.12% in stereo. Capture Ratio: 1.5dB. Image Rejection: 80dB. S/N: 75dB stereo. Alternate Channel Selectivity: 70dB. Separation: 50dB. Spurious Rejection: 100dB.

AM SECTION: Sensitivity: 20uV. Response: 50-6kHz NRSC. Distortion: 0.5%.

Adjacent Channel Selectivity: 45dB. S/N: 60dB. Image Rejection: 78dB.

CABINET: L 70



EARLY







LATE LATE

MR 7084 - Sold from 1995 - 1999. S/N: LP1001~LP???? (EARLY) S/N: NY1001~NY???? (LATE)

Size: 3-5/8"H, 17-1/2"W and 17-1/2"D behind panel. **Weight:** 15 lb. **\$1,500.00**