

MCD 201

SINGLE DISC SACD/CD PLAYER

McIntosh

The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. TRACK \ll BACK / NEXT \gg control. Disc door. IR remote sensor. LEVEL control. \ll HEADPHONES jack. Touch buttons: MUTE (with indicator), SACD/CD, \ll REV, FF \gg . Digital display. ■ STOP, \ll PAUSE, \gg PLAY, OPEN/CLOSE, STANDBY/ON (with indicator).



BACK PANEL: COAXIAL DIGITAL AUDIO OUTPUT. OPTICAL DIGITAL AUDIO OUTPUT. UNBALANCED VARIABLE L & R AUDIO OUTPUT. BALANCED VARIABLE L & R AUDIO OUTPUT. UNBALANCED FIXED L & R AUDIO OUTPUT. BALANCED FIXED L & R AUDIO OUTPUT. IR: sensor input. DATA control IN. POWER CONTROL: OUT and IN. \ll Power cord receptacle.

SPECIFICATIONS: **Response:** 4-110kHz +0.5 -2dB (SACD); 4-20kHz +0.05 - .05dB (CD). **Dynamic Range:** better than 100dB. **Signal to Noise Ratio:** better than 110dBA. **Channel Separation:** better than 98dB. **Distortion:** 0.002% (SACD); 0.003 (CD). **Sampling Rate:** 44.1kHz (CD and MP3). **Fixed Analog Output:** 2.Vrms unbalanced and 4.Vrms balanced. **Variable Analog Output:** 0 - 6.0 Vrms unbalanced and 0 - 12.0 Vrms balanced. **Digital Output:** 0.5V p-p/75 ohm (coaxial), -15dBm to -21dBm (optical). Has **HR056** hand remote.

Power Requirements: 120 Volts, at 35 watts.

MCD 201

SINGLE DISC SACD/CD PLAYER

McIntosh
The Compendium



MCD 201 - Sold from 2005 - 2009. S/N: XD1001~XD???? (? ,???? UNITS)

Size: 6"H, 17-1/2"W and 16-1/2"D behind panel. **Weight:** 22.8 lb. **\$3,300.00**