

MCD 7008

SIX DISC CD CHANGER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature and anodized black aluminum panel. Disc drawer. IR remote SENSOR. Digital display. ⚡ Touch buttons: MEMORY: CANCEL, REVIEW, ENTER, POWER, DATA or MODE, DISC: SINGLE, 1, 2, 3, 4, 5, 6. TRACK: KEYPAD 0 to 9, CLEAR, STORE, PLAY▶, LOAD (with indicator), RANDOM. ◀◀ REV, FF▶▶, BACK, NEXT, STOP, PAUSE, REPEAT, SCAN. VOLUME control. HeadPHONE jack.



BACK PANEL: DIN remote CONTROL connector. DATA IN. DIGITAL OUTPUT: ON or OFF. COAXIAL DIGITAL OUTPUT. ⚡ ANALOG OUTPUT: Left and Right FIXED, Left and Right VARIABLE. Power cord.

SPECIFICATIONS: **Response:** 5-20kHz (+0 -0.3dB). **Dynamic Range:** 100dB. **Signal to Noise Ratio:** 107dBA. **Separation:** 100dB. **Distortion:** 0.002%. **Sampling Rate:** 352.8kHz. **D/A Conversion:** two 20 bit (eight times oversampling with digital filter). **Error Correction:** cross-interleaved Reed Solomon code (CIRC). **Readout:** AlGaAs laser 780nm.

Power Requirements: 120 Volts, at 22 watts. Has **HR7008** hand remote.

CABINET: L 72

MCD 7008

SIX DISC CD CHANGER

McIntosh
The Compendium



MCD 7008 - Sold from 1992 - 1996. S/N: GS1001~GS???? (? ,???? UNITS)

Size: 5-3/8"H, 17-1/2"W and 17-1/2"D behind panel. **Weight:** 24.5 lb. **\$2,200.00**