

MVP 841

SINGLE DISC DVD/CD PLAYER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Disc drawer. IR remote SENSOR. ⚡ Touch buttons: OPEN/CLOSE, ◀ REWIND, ▶ FF, ◀ BACK, NEXT ▶. Digital display. Touch buttons: ■ STOP, || PAUSE, ▶ PLAY, STANDBY/ON (with indicator), POWER: ON or OFF.



BACK PANEL: Power cord receptacle. ⚡ COAXIAL DIGITAL AUDIO OUTPUT. OPTICAL DIGITAL AUDIO OUTPUT. L & R AUDIO OUTPUT. Composite VIDEO OUTPUT. S-VIDEO OUTPUT. VIDEO OUTPUT SELECT: COMPOSITE/S-VIDEO or COMPONENT VIDEO. COMPONENT VIDEO OUTPUT: PR, PB and Y. DATA control input. POWER CONTROL: OUT and IN.

SPECIFICATIONS: **DVD: Response:** 4-22kHz (48K sampling), 4-44kHz (96K sampling). **CD Audio:** 4-20kHz. **Dynamic Range:** >100dB DVD and >98dB CD. **CD Signal to Noise Ratio:** >110dBA. **Channel Separation:** >110dB. **Distortion:** 0.003%. **D/A Converters:** one each 10 bit video converter, one each 96hz/24 bit. **Laser Beam Wavelength:** 665/nm. **Analog Output:** 2.2Vrms. **Digital Output:** 0.5Vp-p (coaxial); -15dBm-21dBm (optical). **Video Output Levels:** (75 ohms): Composite: 1 Vp-p; S-video: Y: 1 Vp-p; C: 0.286 Vp-p; Component: Y: 1 Vp-p, Pb: 0.7 Vp-p; Pr: 0.7 Vp-p. **NTSC Region Code:** 1. **Compatible Disc Types:** DVD-Video, CD-Audio (CD-DA), Video CD. Has **MVP040** hand remote. **Power Requirements:** 120 Volts, at 28 watts.

MVP 841

SINGLE DISC DVD/CD PLAYER

McIntosh
The Compendium



MVP 841 - Sold from 2000 - 2002. S/N: SF1001~SF???? (? ,???? UNITS)

Size: 5-3/8"H, 17-1/2"W and 15"D behind panel. **Weight:** 20 lb. **\$2,750.00**