

MC 1.2KW

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: LED/fiber-optic illuminated green/gold nomenclature. Illuminated POWER OUTPUT meter (linear WATTS or DECIBELS). POWER GUARD LED. ⚡ METER mode switch: LIGHTS OFF, WATTS or HOLD. POWER switch: OFF, REMOTE or ON. Handles.



BACK PANEL: POWER CONTROL jacks: OUT and IN. ⚡ BALANCED audio INPUT. ⚡ BALANCED audio INPUT /OUTPUT. ⚡ UNBALANCED audio INPUT. ⚡ INPUT MODE: UNBALANCED or BALANCED. ⚡ CIRCUIT BREAKER. Speaker OUTPUT connectors: 2 Ω, 4 Ω, 8 Ω, Power cord receptacle. Polished stainless steel chassis.

MC 1.2KW

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 1200w into 2, 4 or 8 ohms. **Response:** 20-20kHz (+0 -0.25dB).
Distortion: 0.005%. **Noise and Hum:** -120dBA unbalanced, -124dBA balanced.
Output impedance: 2, 4 or 8 ohms. **Damping Factor:** >40. **Input Impedance:** 10k. **Input Sensitivity:** 2.5v unbalanced, and 5v balanced. **Dynamic Headroom:** 2 dB. Sentry Monitor. Power Guard. **Autoformer.** Quad Balanced™. **Power Requirements:** 120V at 12 Amps.



MC 1.2KW - Sold from 2008 - 2020. S/N: YF1001~YF???? and ADB-1001~ ADB-????

Size: 12-5/16"H, 17-3/4"W and 22"D. **Weight:** 147 lb.

\$11,000.00