

C 15

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. BASS. TREBLE. BALANCE: L to R. VOLUME. ⚡ IR SENSOR. Touch buttons (with indicator lights): CD 1, CD 2, TUNER, VIDEO, PH/AUX, TAPE. HEADPHONES jack. Touch buttons (with indicator lights): MONO, OUTPUT 1, OUTPUT 2, MUTE, LOUD, STANDBY/ON. POWER: ON or OFF.



BACK PANEL: Power cord receptacle. Coax EXTERNAL SENSOR connector. POWER CONTROL jack. DATA PORTS: VIDEO / SUM, TUNER / HOME, CD 2 / TAPE, CD 1 / AUX. OUTPUTS: 2, 1 and TAPE. PROCESSOR FROM. PROCESSOR switch IN or OUT. PROCESSOR TO. INPUTS: TAPE, VIDEO, TUNER, CD 2, CD 1, PH/AUX. Ground binding post. Switch: PH or AUX.

SPECIFICATIONS: **Response:** 20-20kHz (+0 -0.5dB). **Distortion:** 0.002%. **Noise and Hum:** -105dB high level, -90dB phono. **Output Impedance:** 600 ohms. **Input Sensitivity and Impedance:** high level 0.25V (10V max) and 22k, phono 2.5mV (90mV max) at 47k and 65pF. **Tone Controls:** bass and treble boost and cut 12dB. Electromagnetically switched inputs. **Power Requirements:** 120V at 25 Watts. Uses **HR033** hand remote control and **HR093** replacement.



C 15

STEREO PRE-AMPLIFIER

McIntosh
The Compendium



C 15 - Sold from 1998 - 2000. S/N: PV1001 ~ PV????

Size: 5-3/8"H, 17-1/2"W and 17-1/2"D behind panel. **Weight:** 14.5 lb. **\$1,500.00**